

## PM 6685 PM 6685R

Technical Data

### Universal Frequency Counter Rubidium Frequency Counter Calibrator

**Cal lab performance you can take anywhere**

**Cal lab performance in the field**  
The PM 6685 frequency counter from Fluke brings cal lab accuracy to field measurements. With 10 digits per second, plus overflow (displays 11th and 12th digits), it delivers high-accuracy measurements instantly. The PM 6685 is easy to use, compact and - most important of all - it has today's smartest input triggering for frequency measurements. The battery option for the PM 6685 maintains oven stability for 20 hours, giving you instant oven performance even after long transportation.



#### PM 6685

- 300 MHz basic input range; options for 1.3 GHz, 2.7 GHz, 4.2 GHz or 4.5 GHz
- Ultra High Stability Oven: up to  $5 \times 10^{-9}$  within 10 min
- Battery supply in combination with Ultra High Stability Oven for On-Site calibration
- Displays 10 digits in a second
- Smart AUTO trigger eliminates guesswork, provides error-free measurements
- Analog Bar Graph displays signal strength and input sensitivity to assist instrument setup and RF tuning

- applications  
Nulling function lets you use any value as input reference
- Digit blanking function to eliminate distracting or insignificant digits in your readings
- Connect-and-go convenience for testbench and field use  
Optional IEEE-488 (SCPI) interface

#### GSM Network operators

Depending on the cellular radio system network operators and the internal procedures and

budgets, the calibration requirement can be fulfilled with the following solutions from Fluke.

- PM6685 with the Ultra-High-Stability oven oscillator in the small housing with or without battery supply to check base stations, offering a low initial cost-effective solution (2 month calibration interval for a margin of 5x better than GSM specification)
- PM6685R **Rubidium** Frequency Counter/Calibrator, to check base stations,

providing low cost of ownership, (2 year calibration interval, for a margin of 50x better than GSM specification)

### New Ultra High Stability Timebase

The new Ultra-High-Stability oven oscillator PM9692 fills the gap between the currently available best crystal oscillators and the Rubidium oscillator. The short warm-up time of 10 min to reach  $5 \times 10^{-9}$  of final value makes it the ideal solution for many ion-site calibration applications.

The PM9692 oscillator in the smaller housing of the PM6685, provides adequate accuracy to handle the fast-growing need for calibrations of digital cellular

telephony systems and other calibration applications, very cost effectively.

### PM6685R - Today's most accurate frequency counter

The PM 6685R from Fluke is the most accurate portable frequency counter on the market. It offers all the functionality of the PM 6685, plus the stability and accuracy of a built-in Rubidium atomic reference.

High stability, high accuracy and short warm-up times make this instrument ideal for high-accuracy calibration procedures outside the cal lab environment, such as in base station transmitters of large telecommunication networks

like GSM.

The short warm-up time means that the PM 6685R is ready for use within minutes after field transport or a change of location inside a building.

### Additional features PM 6685R

- High accuracy and short warm-up times:
  - $1 \times 10^{-9}$  within 7 min.
  - $4 \times 10^{-10}$  within 10 min.
  - Ageing  $2 \times 10^{-10}$  per year
- Calibrates any application specific frequency
- 10 MHz buffered Rubidium reference output
- 5 year warranty on Rubidium element

### Technical Specifications PM 6685 Measuring Functions

Refer to table 1 for measurement uncertainty information.

#### Frequency A, C

Range	
Input A:	10 Hz to 300 MHz
Input C:	70 MHz to 1.3 GHz (PM 9621) 100 MHz to 2.7 GHz (PM 9624) 150 MHz to 4.2 GHz (PM 9625B) 150 MHz to 4.5 GHz (PM 9625)
Resolution:	10 digits/s measurement time

#### Burst Frequency A

Frequency Range:	100 Hz to 160 MHz
PRF Range:	1 Hz to 100 kHz
Pulse Width Range:	1 $\mu$ s to 50 ms, min. 3 periods of this signal

#### Period A

Range:	6 ns to 100 ms
Resolution:	10 digits/s measurement time

#### Ratio A/E, C/A

Range:	$10^{-7}$ to $10^{10}$
Frequency Range:	
Input A:	10 Hz to 160 MHz
Input E:	10 Hz to 50 MHz
Input C:	70 MHz to 1.3 GHz (PM 9621) 100 MHz to 2.7 GHz (PM 9624) 150 MHz to 4.2 GHz (PM 9625B) 150 MHz to 4.5 GHz (PM 9625)

#### Pulse Width A

Range:	3 ns to 10 ms
Frequency Range:	50 Hz to 160 MHz
Voltage Range:	100 mV p-p to 70V p-p

#### Duty Factor A

Range:	0 to 1
Frequency Range:	50 Hz to 160 MHz
Voltage Range:	100 mV p-p to 70V p-p

#### Totalize A

Event counting on input A with manual start and stop

Range:	0 to $10^{17}$ 0 to 160 MHz
--------	--------------------------------

### Input and Output Specifications

#### Input A

Frequency Range:	10 Hz to 300 MHz
Coupling:	AC
Impedance:	1 M $\Omega$ /25 pF or 50 $\Omega$ , VSWR < 2:1
<b>Sensitivity:</b>	
Sinewave:	10 mV rms, 10 Hz to 50 MHz 15 mV rms, 50 MHz to 100 MHz 20 mV rms, 100 MHz to 150 MHz 30 mV rms, 150 MHz to 200 MHz 50 mV rms, 200 MHz to 300 MHz 50 mV p-p, 3 ns minimum pulse width 30 mV p-p to 70V p-p
Pulse:	
Dynamic Range:	

#### Manual Trigger:

Sensitivity Range: 10 mV rms to 10V rms, variable in 3 dB steps, indicated on a bar graph

Trigger Level: Selectable for optimum triggering on waveforms with duty factors <0.25, 0.25 to 0.75 and >0.75

Trigger Slope: Positive or negative  
**Auto Trigger:** Automatic setting of input signal conditioning circuits for optimum triggering on different amplitudes and waveforms

Frequency: Minimum 50 Hz  
Sensitivity Range: 10 mV rms to 25V rms  
Signal Monitor: A bar graph displays actual input signal level in 3 dB steps, 10mV rms to 10V rms

#### Low Pass Filter:

100 kHz nominal 3 dB point. Minimum 40 dB attenuation at 1 MHz.

#### Damage Level:

1 M $\Omega$ : 350V (dc + ac peak) at dc to 440 Hz, falling to 12V rms at 1 MHz and above 50 $\Omega$ : 12V rms

**Input C (Option PM 9621)**

Frequency Range:	70 MHz to 1.3 GHz
Prescaler Factor:	256
Operating Input Voltage Range:	
70 to 900 MHz:	10 mV rms to 12V rms
900 to 1100 MHz:	15 mV rms to 12V rms
1100 to 1300 MHz:	40 mV rms to 12V rms
Amplitude Modulation:	dc to 0.1 MHz: Up to 94% depth 0.1 to 6 MHz: Up to 85% depth Minimum signal must exceed minimum operating input voltage
Impedance:	50Ω nominal, ac coupled, VSWR <2:1
Max Voltage without Damage:	12V rms, pin-diode protected
Connector:	BNC

**Input C (Option PM 9624)**

Frequency Range:	100 MHz to 2.7 GHz
Prescaler Factor:	16
Operating Input Voltage Range:	
100 MHz to 300MHz	20 mV rms to 12V rms
0.3 GHz to 2.5 GHz	10 mV rms to 12V rms
2.5 GHz to 2.7 GHz	20 mV rms to 12V rms
Amplitude Modulation:	As PM 9621
Impedance:	50 nominal, ac coupled, VSWR <2.5:1
Max Voltage without Damage:	12V rms, pin-diode protected
Connector:	Type N Female

**Input C (Option PM 9625B)**

Frequency Range:	150 MHz to 4.2 GHz
Prescaler Factor:	32
Operating Input Voltage Range:	
150 to 300 MHz:	20 mV rms to 1V rms (-21 to +13 dB)
0.3 to 2.2 GHz:	10 mV rms to 1V rms (-27 to +13 dB)
2.2 to 3.5 GHz:	15 mV rms to 1V rms (-23.5 to +13 dB)
3.5 to 4.2 GHz:	25 mV rms to 1V rms (-19 to +13 dB)
Amplitude Modulation:	As PM9621
Impedance:	50 nominal, AC coupled, VSWR <2.5:1
Max Voltage without damage:	12V rms, pin-diode protected
Connector:	Type N Female

**Input C (Option PM 9625)**

Frequency Range:	150 MHz to 4.5 GHz
Prescaler Factor:	32
Operating Input Voltage Range:	
150 to 300 MHz:	20 mV rms to 1V rms (-21 to +13 dBm)
0.3 to 2.5 GHz:	10 mV rms to 1V rms (-27 to +13 dBm)
2.5 to 3.7 GHz:	15 mV rms to 1V rms (-23.5 to +13 dBm)
3.5 to 4.5 GHz:	25 mV rms to 1V rms (-19 to +13 dBm)
Amplitude Modulation:	As PM 9621
Impedance:	50 nominal, ac coupled, VSWR 2,5:1 typical
Max Voltage	

without Damage:	12V rms (+34 dBm), pin-diode protected
Connector:	Type N Female

**External Reference Input D**

The use of external reference is indicated on the display	
Input Frequency:	10 MHz standard. 1 MHz and 5 MHz with optional Reference Frequency Multiplier (PM 9697).
Voltage Range:	500 mV rms to 10V rms
Impedance:	Approx 1 k (ac coupled)

**Input E**

Used in Ratio A/E and external arming/gating modes	
Frequency Range:	DC to 50 MHz
Pulse Width:	10 ns minimum
Slew Rate:	2V/μs minimum
Trigger Level:	TTL level, 1.4V nominal
Trigger Slope:	Positive or negative
Impedance:	Approx 2 kΩ (dc coupled)
Damage Level:	±25V peak

**Reference Output G**

Frequency:	10 MHz, sine wave
Output Level:	>0.5V rms into 50Ω load, >0.7V rms into high impedance load
Coupling:	AC

**Auxiliary Functions****External Arming/External Gate**

External signal on input E can be used to inhibit start and/or stop triggering.	
Stop arming is not applicable to Pulse Width and Duty Factor measuring modes.	
Start Arming Delay:	OFF or 200 ns to 1.6s in 100 ns steps

**Nulling/Frequency Offset**

Nulling enable measurements to be displayed relative to a previously measured value or any frequency offset value entered via front panel keys	
--	--

**Other Functions**

Measuring Time:	Single cycle, 0.8, 1.6, 3.2, 6.4, 12.8 μs and 50 μs to 20s, (up to 400s, depending on measuring function and input signal frequency)
Local/Preset:	Go to local function in remote mode, or preset counter to default setting in local mode
Restart:	Starts a new measurement
Display Hold:	Freezes measuring result. Start and stop of the totalization in TOT A MAN.
Check:	Applies 10 MHz to the measuring logic
Display:	LCD with high-luminance backlight
Number of Digits:	10 digits plus exponent
Blanking:	Least significant digits can be blanked
Bar graph:	Displays input signal level or sensitivity setting in 3 dB steps from 10mV rms to 10V rms
Auxiliary Menu:	The following functions are available from the AUX MENU and via the GPIB interface
Save/Recall:	19 complete instrument settings. 10 settings can be user protected
GPIB-Address:	Read and temporarily change

Burst Frequency:	via front panel keys. (Set new address on rear panel switch.) A or C (PM 9625) input, set synchronization delay time	Display Overflow:	Display of the 11th and 12th digits
PRF:	A or C (PM 9625) input, set synchronization delay time	Test:	Select selftests
Trigger Slope:	Positive or negative slope	Program Version:	Display instrument and GPIB program versions
Arming Start:	Positive or negative slope, set start arming delay time	Time Out:	OFF or 100 ms to 25.5s in 100 ms steps
Arming Stop:	Positive or negative slope	Analog Output:	Select digits and scaling factor
Null:	Read and change stored offset frequency	Display Backlight:	On/Off

Measuring function	Random Uncertainty rms	Systematic Uncertainty	LSD Displayed
Frequency Period	$\pm \frac{\sqrt{(250\text{ps})^2 + (\text{Trigger Error})^2}}{\text{Measuring Time}} \times \text{Freq. or Period}$	$\pm \text{Time Base Error} \times \text{Freq. or Period}$	$\frac{250\text{ps} \times \text{Freq. or Period}}{\text{Measuring Time}}$
Ratio $f_1/f_2$	$\pm \frac{\sqrt{(\text{Prescaler Factor})^2 + (f_1 \times \text{Trigger Error of } f_2)^2}}{f_2 \times \text{Measuring Time}}$		$\frac{\text{Prescaler Factor}}{f_2 \times \text{Measuring Time}}$
Pulse Width (Auto Trigger)	$\pm \sqrt{(250 \text{ ps})^2 + (\text{Trigger Error})^2}$	$\pm \text{Time Base Error} \times \text{Pulse Width}$ $\pm 0.5 \times \text{Transition Time} \pm 1.5 \text{ ns}$	100 ps
Duty Factor	$\pm \sqrt{(250 \text{ ps})^2 + (\text{Trigger Error})^2} \times \text{Frequency}$	$\pm (0.5 \times \text{Transition Time} \pm 1.5 \text{ ns})$ $\times \text{Frequency}$	$1 \times 10^{-6}$

Table 1. Measurement Uncertainties and LSD Displayed

**Random Uncertainty**

Random uncertainty is due to quantization error, short-term Time Base stability, internal noise and input signal noise. The random uncertainty can be reduced by increasing the measurement time. Trigger Error: Internal noise and input signal noise, expressed as an rms Trigger Error.

$$\text{Trigger Error} = \frac{1.4 \times \sqrt{(e_{\text{amp}})^2 + (e_n)^2}}{\text{Signal slew rate (V/s) at trigger point}}$$

Where:

$e_{\text{amp}}$  = rms input amplifier noise (250  $\mu\text{V}$  rms typical)

$e_n$  = rms noise of the input signal over a 300 MHz bandwidth

**Systematic Uncertainty**

See crystal oscillator specifications for aging and possible frequency deviation due to the oscillator's temperature dependency

**LSD Displayed**

Unit value of Least Significant Digit (LSD) displayed. After calculation, the LSD value is rounded to the nearest decade before display (for example  $>0.5 \text{ Hz}$  will be 1 Hz and  $<0.5 \text{ Hz}$  will be 0.1 Hz). LSD blanking is available to reduce displayed resolution. Measuring times  $>1\text{s}$  can give significance in  $> 10$  digits. The 11th and 12th digits can be displayed using the display overflow function.

**Options**

**Battery Unit (Option PM 9623)**

The PM 9623 is a rechargeable battery unit for mounting inside the counter.

**Battery Type:** Sealed lead-acid cells

**Battery Capacity:** At 25C

Standby Mode: Typically 20 hours with Oven Time Base

Operating Mode: Typically 3 hours without options, 2.5 hours with Oven Time Base, and 2 hours with Oven Time Base and Input C

**Recharge Time:** Typically 8 hours in standby mode

Battery Protection: Overcharge and deep discharge protection

External DC: 12V to 24V via socket on rear panel (16V to 24V to charge internal battery)

Line Failure Protection: Counter automatically switches to internal battery or external dc when the line voltage falls below 90V ac

Temperature

Operating: 0°C to +40°C

Storage: -40°C to +50°C

Weight: 1.5 kg (3.3 lb)

**GPIB (Option PM 9626/02)**

Programmable Functions: All front panel and AUX MENU functions  
 Compatibility: IEEE 488.2-1987, SCPI 1991.0  
 Interface Functions: SH1, AH1, T6, L4, SR1, RL1, DC1, DT1, E2  
 Maximum Measurement Rate to Internal Memory: 200 to 1600 readings/s, depending on measurement function and internal data format  
 Internal Memory Size: 764 to 2600 readings, depending on measurement function and internal data format

Maximum Bus Transfer Rate from internal memory: 150 to 1000 readings/s, depending on internal data format and output data format  
 Data Output Format: ASCII, IEEE double precision floating point  
 Time Out: Off or 100 ms to 25.5s in 100 ms steps  
 Analog Output: 0 to 4.98V in 20 mV steps, derived from three consecutive digits selected from the measurement result  
 Output Impedance: 200Ω

**Timebase Options**

Option model:	PM668-/-1-	PM668-/-2-	PM668-/-4-	PM668-/-5-	PM668-/-6-	PM668-/-7-
Retro-fittable option:	non retrofit.	PM9678B/021	PM9690/011	PM9691/011	PM9692/011	non retro-fit.
Time base type:	Standard	TCXO	OCXO	OCXO	OCXO	Rubidium
<b>Uncertainty due to:</b>						
Calibration adjustment tolerance, at + 23°C ± 3°C	<1x10 <sup>-6</sup>	<2x10 <sup>-7</sup>	<5x10 <sup>-8</sup>	<2x10 <sup>-8</sup>	<5x10 <sup>-9</sup>	<5x10 <sup>-11</sup>
Ageing:						
per 24 hr.	n.a.	n.a.	<1.5x10 <sup>-9</sup> ❶	<5x10 <sup>-10</sup> ❶	<3x10 <sup>-10</sup> ❶	n.a.
per month	<5x10 <sup>-7</sup>	<1x10 <sup>-7</sup>	<2x10 <sup>-8</sup>	<1x10 <sup>-8</sup>	<3x10 <sup>-9</sup>	<5x10 <sup>-11</sup> ❷
per year	<5x10 <sup>-6</sup>	<5x10 <sup>-7</sup>	<1x10 <sup>-7</sup>	<7.5x10 <sup>-8</sup>	<2x10 <sup>-8</sup>	<2x10 <sup>-10</sup> ❸
Temperature variation:						
0°C-50°C,	<1x10 <sup>-5</sup>	<1x10 <sup>-6</sup>	<1.5x10 <sup>-8</sup>	<5x10 <sup>-9</sup>	<2.5x10 <sup>-9</sup>	<3x10 <sup>-10</sup>
20°C-26°C (typ. values)	<3x10 <sup>-6</sup>	<2x10 <sup>-7</sup>	<2x10 <sup>-9</sup>	<6x10 <sup>-10</sup>	<4x10 <sup>-10</sup>	<5x10 <sup>-11</sup>
Power voltage variation: ± 10%	<1x10 <sup>-8</sup>	<1x10 <sup>-9</sup>	<5x10 <sup>-10</sup>	<5x10 <sup>-10</sup>	<5x10 <sup>-10</sup>	<1x10 <sup>-11</sup>
<b>Short term stability:</b>						
τ = 1 s					<1x10 <sup>-11</sup>	<5x10 <sup>-11</sup>
(root Allan Variance)					<3x10 <sup>-12</sup>	<1.5x10 <sup>-11</sup>
τ = 10 s	not specified	not specified	not specified	not specified	<1x10 <sup>-12</sup>	<5x10 <sup>-12</sup>
τ = 100 s						
<b>Power-on stability:</b>						
Deviation versus final value after 24hr on time, after a warm-up time of:	n.a.	n.a.	<1x10 <sup>-7</sup>	<1x10 <sup>-7</sup>	<5x10 <sup>-9</sup>	<4x10 <sup>-10</sup>
30 min	30 min	30 min	15 min	15 min	10 min	10 min
<b>Total uncertainty, for operating temperature</b>						
0°C to 50°C, at 2σ (95%) confidence interval:						
1 year after calibration	<1.2x10 <sup>-5</sup>	<1.2x10 <sup>-6</sup>	<1.5x10 <sup>-7</sup>	<1x10 <sup>-7</sup>	<2.5x10 <sup>-8</sup>	<7x10 <sup>-10</sup>
2 years after calibration	<1.5x10 <sup>-5</sup>	<1.5x10 <sup>-6</sup>	<2.5x10 <sup>-7</sup>	<2x10 <sup>-7</sup>	<5x10 <sup>-8</sup>	<9x10 <sup>-10</sup>
<b>Typical total uncertainty, for operating temperature</b>						
20°C to 26°C, at 2σ (95%) confidence interval:						
1 year after calibration	<7x10 <sup>-6</sup>	<7x10 <sup>-7</sup>	<1.5x10 <sup>-7</sup>	<1x10 <sup>-7</sup>	<2.5x10 <sup>-8</sup>	<6x10 <sup>-10</sup>
2 years after calibration	<1.2x10 <sup>-5</sup>	<1.2x10 <sup>-6</sup>	<2.5x10 <sup>-7</sup>	<2x10 <sup>-7</sup>	<5x10 <sup>-8</sup>	<8x10 <sup>-10</sup>

n.a.

Not discernible, neglectable versus 1°C temperature variation.

❶ After 48 hours of continuous operation, PM9692 typical value 1 x 10<sup>-10</sup> / 24h

❷ after 1 month of continuous operation

❸ after 1st year, ageing during 1st year: < 5 x 10<sup>-10</sup>

**Explanation**

Calibration Adjustment Tolerance is the maximal tolerated deviation from the true 10MHz frequency after a calibration. When the reference frequency does not exceed the tolerance limits at the moment of calibration, an adjustment is not needed. Total uncertainty is the total possible deviation from the true 10MHz value under influence of frequency drift due to ageing and ambient temperature variations versus the reference temperature. The operating temperature range and the calibration interval are part of this specification.

**General Specifications**

**Environmental Conditions**

Temperature  
 Operating: 0C to +50C  
 Fan option PM 9628/02 is required when ambient temperature >45C and oven oscillator PM 9690, 9691 or 9692 is installed  
 Storage: -40°C to +70°C  
 Humidity: 95% RH, 0°C to 30°C  
 Altitude Operating: Up to 4600m (15000 ft)  
 Non-operating: Up to 12000m (40000 ft)  
 Vibration: 3G at 55 Hz per MIL-T-28800D, Class 3, Style D  
 Shock: Half-sine 40G per MIL-T-28800D, Class 3, Style D. Bench handling.

**Reliability:**

Safety: Shipping container. MTBF 30 000 hours  
 IEC 1010 Class 1, CSA 22.2 No. 231, EN61010, CE  
 EMC: EN 55011, VDE 0871 Level B, FCC Part 15J Class A, CE

**Power Requirements**

AC: 90 to 265V rms, 45 to 440 Hz, max 30W  
 DC (PM 9623): Internal battery or external 12 to 24V dc, max 2A

**Mechanical Data**

Width: 210 mm (8.25 in)  
 Height: 86 mm (3.4 in)  
 Depth: 395 mm (15.6 in)

Weight: Net 3.2 kg (7 lb); shipping  
5.5 kg (12 lb)

### Additional Specification for PM6685R

(where these differ from the standard model PM6685)  
Short-term (Root Allan Variance of reference Oscillator)  
See Timebase Options table

### Warm-up time (at 25°C)

Unlocked status indicated by LED  
Time to lock approx. 5 min.  
Time to reach  
1 x 10<sup>-9</sup> approx. 7 min.  
Retrace: < 2.5 x 10<sup>-11</sup>

### Power requirements (at 25°C)

Voltage 90 ... 264 Vrms, 47 ... 440Hz  
Power rating <100W for <4 min., 47W  
continuous operating

### Dimensions and weight

Width 315 mm (12.4 in)  
Weight Net 5.5 kg (12 lb)  
Shipping weight 8.8 kg ( 19 lb)

### Ordering Information

#### Basic Model

PM 6685/O11 Universal Frequency Counter  
300 MHz incl.  
Standard Time Base

#### Rubidium Reference Basic Model

PM 6685R/O71 Rubidium Frequency  
Counter/Calibrator  
*Included with Instrument* One year product warranty, line  
cord, operator manual, and  
Certificate of Calibration practices

#### Input Frequency Options

PM 6685/\_4\_ 1.3 GHz Input C (PM 9621)  
PM 6685/\_6\_ 2.7 GHz Input C (PM 9624)  
PM 6685/\_8\_ 4.2 GHz Input C (PM 9625B)  
PM 6685/\_7\_ 4.5 GHz Input C (PM 9625)

#### Time Base Options

PM 6685/\_1\_ Standard Time Base  
PM 6685/\_2\_ TCXO (PM 9678B)  
PM 6685/\_4\_ High Stability Oven Time Base  
(PM 9690)  
PM 6685/\_5\_ Very High Stability Oven Time  
Base (PM 9691)  
PM 6685/\_6\_ Ultra-High-Stability Oven Time  
Base (PM 9692)  
PM 6685R/\_7\_ Rubidium Time Base 1)  
PM 6685/\_8\_ Standard Time Base plus  
External Ref. Frequency  
Multiplier (1, 5, 10 MHz)  
(PM 9697)

1) Product physical dimensions are larger with rubidium time base. The  
rubidium time base is not customer installable.

#### Battery Unit and GPIB Interface Options

PM 6685/\_ \_1\_ or No Battery Unit or GPIB  
PM 6685R/\_ \_1\_ Interface  
PM 6685/\_ \_3\_ Battery Unit (PM 9623)  
PM 6685/\_ \_6\_ or GPIB Interface (PM 9626/O2)  
PM 6685R/\_ \_6\_ and Time & Frequency Analysis  
SW: TimeView  
PM 6685/\_ \_8\_ Battery Unit plus GPIB Interface

#### Example, Ordering Configuration

To order the 300 MHz PM 6685 version with the TCXO Time  
Base and GPIB interface, select the Complete Model Number PM  
6685/O26

#### Options and Accessories

PM 9621 1.3 GHz Input C  
PM 9624 2.7 GHz Input C  
PM 9625B 4.2 GHz Input C  
PM 9625 4.5 GHz Input C

PM 9678B/O1  
PM 9690/O1  
PM 9691/O1  
PM 9692/O1  
PM 9697/O0 \*\*

PM 9623 \*\*\*  
PM 9626/O2 \*  
PM 9622/O0  
PM 9622/O2  
PM 9622/O3  
PM 9628/O2  
PM 9627B  
PM 8929/191  
PM 8911/O91

\* PM9626 GPIB-Interface includes Analog Output and TimeView  
Analysis software

\*\* PM 9697 External Reference Multiplier can be used only with  
the Standard Time Base.

\*\*\* PM 9623 can not be fitted in PM 6685R

*When ordered together with the basic counter, options are factory  
installed.*

*Options ordered separately can be customer retrofitted, except PM 9611/80  
Rear Panel Inputs*

#### SW Drivers MET/CAL HPVEE Manuals

PM6685  
PM6685  
PM6685

on request  
procedures are available  
driver is available

Operator \*  
Program \*  
Service

\* No charge with purchase of unit

#### Factory Warranty

One year product warranty  
Five year warranty on  
Rubidium Element