

APS-7000E Series



FEATURES

- 4.3" large LCD Display
- Output Capacity:
APS-7050E(500VA, 310Vrms, 4.2/2.1Arms)
APS-7100E(1000VA, 310Vrms, 8.4/4.2Arms)
- Measurement Function :
Voltage, Current, Power, Frequency, Power Factor, Ipeak
- Reverse Current Alarm Function
- 10 Sets of The Test Mode Simulate Power Transient Output
- 10 Sets of Preset Allow Users to Store Ten Settings
- OCP/OPP/OTP Protection
- Variable Voltage, Frequency and Current Limiter
- Universal Power Inlet



GW Instek launches the APS-7000E Series the economy version of the APS-7000 Series programmable AC power source. With the height of 2U, the maximum rated output for APS-7050E is 500VA, 310Vrms, 4.2Arms and APS-7100E is 1000VA, 310Vrms, 8.4Arms.

The output frequency range of the series is 45~500Hz. The series is ideal for the test and development of DC power supply devices, consumer electronics, automotive electronics and electronic components.

The APS-7000E Series comprises six measurement and test functions (Vrms, Irms, F, Ipk, W, PF), and provides user interface similar to that of AC Power Meter. The APS-7000E Series, via switching many sets of current levels to increase small current measurement resolution, is ideal for the LED industry and standby mode power consumption test. Ten sets of Preset allow users to store ten settings.

To meet the test criteria of line voltage fluctuation often seen in consumer electronics, the APS-7000E Series not only provides a stable AC power source but also features the Test mode to satisfy special or abnormal voltage and frequency variation demands. Ten sets of the Test mode simulate power outage, voltage rise, and voltage fall. The APS-7000E Series that simulates waveforms of city power grid's transient changes is suitable for verifying electronics products operated under abnormal power source.

The APS-7000E Series is the economy version of the APS-7000 Series. If communications interface and larger voltage/frequency are required, please refer to the APS-7000 Series.



Europe Type Output Outlet



APS-7100E Rear Panel



APS-7050E Rear Panel

APPLICATIONS

- The Broad Power Output Range of The Series is Ideal for Various Power Supply Manufacturers
- The Development of Electronic Components and Testing Applications for Manufacturers
- Incoming Quality Control and R & D Applications
- Small AC Current Measurement Applications

APS-7000E Series

SPECIFICATIONS			
Model		APS-7050E	APS-7100E
Power Rating		500VA	1000VA
Output Voltage		0 ~ 155Vrms/0 ~ 310.0 Vrms	0 ~ 155Vrms/0 ~ 310.0 Vrms
Output Frequency		45.00 ~ 500.0 Hz	45.00 ~ 500.0 Hz
Maximum Current (r.m.s)	0~155Vrms	4.2A	8.4A
Maximum Current (peak)	0~310Vrms	2.1A	4.2A
	0~155Vrms	16.8A	33.6A
	0~310Vrms	8.4A	16.8A
Total Harmonic Distortion (THD)		≤0.5% at 45 ~ 500Hz (Resistive Load)	
Crest Factor		≤4	
Line Regulation		0.1% (% of full scale)	
Load Regulation		0.3% (% of full scale)	
Response Time		<100 μs	
Reverse Current		30% of Maximum Output RMS Current (Continue); 100% of Maximum Output RMS Current (Within 3 minutes)	
SETTING			
Voltage	Range	0 ~ 155Vrms/0 ~ 310Vrms/Auto	
	Resolution	0.01V at 0.00 ~ 99.99Vrms; 0.1V at 100.0 ~ 310.0Vrms	
	Accuracy	±(0.5% of setting+2 counts)	
Frequency	Range	45 ~ 500Hz	
	Resolution	0.01Hz at 45.00 ~ 99.99Hz/0.1Hz at 100.0 ~ 500.0Hz	
	Accuracy	±0.02% of setting	
MEASUREMENT			
Voltage(RMS)	Range	0.20~38.75Vrms/38.76~77.50 Vrms/77.51~155.0Vrms/155.1~310.0Vrms	
	Resolution	0.01V at 0.00 ~ 99.99Vrms; 0.1V at 100.0 ~ 310.0Vrms	
	Accuracy	±(0.5% of reading + 2 counts)	
Frequency	Range	45 ~ 500Hz	
	Resolution	0.01Hz (at 45Hz~99.99Hz)/0.1Hz (at 100Hz~500.0Hz)	
	Accuracy	±0.1Hz	
Current(RMS)	Range	2.00 ~ 70.00mA/60.0 ~ 350.0mA/0.300 ~ 3.500A/3.00 ~ 17.5A	
	Resolution	0.01mA, 0.1mA, 0.001A, 0.01A	
	Accuracy	±(0.6% of reading+5 counts); 2.00~350.0mA/±(0.5% of reading+5 counts); 0.350~3.500A/±(0.5% of reading+3 counts); 3.500~17.50A	
Current(Peak)	Range	0.0 ~ 70.0A	
	Resolution	0.1A	
	Accuracy	±(1% of reading+1 count)	
Power(W)	Resolution	0.01W, 0.1W, 1W	
	Accuracy	±(0.6% of reading+5 counts); 0.20~99.99W; ±(0.6% of reading+5 counts); 100.0~999.9W ±(0.6% of reading+2 counts); 1000~9999W	
Power Factor	Resolution	0.001	
	Accuracy	±(2% of reading + 2 counts)	
GENERAL			
Number of Preset		10(0~9 Numeric keys)	
Protection		OCP, OPP, OTP and Alarm	
ENVIRONMENT CONDITIONS			
Operation Temperature		0 ~ +40°C	
Storage Temperature		-10 ~ +70°C	
Operating Temperature		20 ~ 80% RH (No Condensation)	
Storage Humidity		80% RH or less(No Condensation)	
AC INPUT			
Input Power Source		1φ AC 115/230Vac ±15%	
DIMENSIONS & WEIGHT			
		430(W) x 88(H) x 400(D) mm; Approx. 24kg	430(W) x 88(H) x 560(D) mm; Approx. 38kg

Specifications subject to change without notice. PS-7000EGD2DH

ORDERING INFORMATION	
APS-7050E	500VA AC Power Source
APS-7100E	1000VA AC Power Source

ACCESSORIES
CD ROM (User Manual x 1), Power Cord (Region Dependent), Mains Terminal Cover Set, GTL-123 Test Lead
OPTIONAL ASSESSORIES
GRA-423 Rack Mount Kit (APS-7000E Series)

Global Headquarters
GOOD WILL INSTRUMENT CO., LTD.
 T +886-2-2268-0389 F +886-2-2268-0639

China Subsidiary
GOOD WILL INSTRUMENT (SUZHOU) CO., LTD.
 T +86-512-6661-7177 F +86-512-6661-7277

Malaysia Subsidiary
GOOD WILL INSTRUMENT (SEA) SDN. BHD.
 T +604-6111122 F +604-6115225

Europe Subsidiary
GOOD WILL INSTRUMENT EURO B.V.
 T +31(0)40-2557790 F +31(0)40-2541194

U.S.A. Subsidiary
INSTEK AMERICA CORP.
 T +1-909-399-3535 F +1-909-399-0819

Japan Subsidiary
TEXIO TECHNOLOGY CORPORATION.
 T +81-45-620-2305 F +81-45-534-7181

Korea Subsidiary
GOOD WILL INSTRUMENT KOREA CO., LTD.
 T +82-2-3439-2205 F +82-2-3439-2207

India Subsidiary
GW INSTEK INDIA LLP.
 T +91-80-6811-0600 F +91-80-6811-0626

GW INSTEK
 Simply Reliable



Website

Facebook

LinkedIn