

# NI ELVIS™ II Series Specifications

The specifications in this document refer to both the NI ELVIS II and the NI ELVIS II+ unless otherwise noted. These specifications are typical after a 30 minute warm-up time, at 25 °C, unless otherwise noted.

## Analog Input

Number of channels .....	8 differential or 16 single ended
ADC resolution .....	16 bits
DNL .....	No missing codes guaranteed
INL .....	60 ppm max
Absolute accuracy .....	Refer to the <i>AI Absolute Accuracy Table</i>
Sample Rate	
Maximum .....	1.25 MS/s single channel, 1.00 MS/s multi channel (aggregate)
Minimum .....	No minimum
Timing accuracy .....	50 ppm of sample rate
Timing resolution.....	50 ns

## Settling Time for Multichannel Measurements

Range	10 LSB for full scale	1 LSB for full scale
10 V, 5 V, 2 V, 1 V, 0.5 V	1 µs	2 µs
0.2 V, 0.1 V	2 µs	8 µs

Input coupling .....	DC
Input range .....	±10 V, ±5 V, ±2 V, ±1 V, ±0.5 V, ±0.2 V, ±0.1 V
Maximum working voltage for analog inputs (signal + common mode) .....	±11 V of AIGND
CMRR (DC to 60 Hz) .....	90 dB

Crosstalk @100 kHz (adjacent channel) .....	-70 dB
(non-adjacent channel).....	-80 dB
Input Impedance	
Device on AI+ or AI- to AIGND .....	>10 GΩ    100 pF
Device off AI+ or AI- to AIGND .....	820 Ω
Input bias current .....	±100 pA
Small signal bandwidth (-3 dB).....	1.2 MHz
Input FIFO size.....	4095 samples
Scanlist memory .....	4095 entries
Data transfers.....	USB signal stream, programmed I/O

## Overshoot Protection (AI±, AISENSE)

Device on .....	±25 V for up to four lines
Device off .....	±15 V for up to four lines
Input current during overshoot condition.....	±20 mA max per line

## Analog Triggers

Number of triggers .....	1
Source .....	AI<0..15>, ScopeCH0, ScopeCH1
Functions .....	Start Trigger, Reference Trigger, Pause Trigger, Sample Clock, Convert Clock, Sample Clock Timebase
Source level .....	± Full scale
Resolution.....	10 bits

Accuracy ..... 1%  
Modes ..... Analog edge triggering,  
analog edge triggering  
with hysteresis, and  
analog window triggering

## Arbitrary Waveform Generator/Analog Output

Number of channels ..... 2  
DAC resolution ..... 16 bits  
DNL .....  $\pm 1$  LSB  
Monotonicity ..... 16 bit guaranteed  
Accuracy ..... Refer to the *AO Absolute Accuracy (No Load) Table*  
  
Maximum update rate  
    1 channel ..... 2.8 MS/s  
    2 channels ..... 2.0 MS/s  
  
Timing accuracy ..... 50 ppm of sample rate  
Timing resolution ..... 50 ns  
Output range .....  $\pm 10$  V,  $\pm 5$  V  
Output coupling ..... DC  
Output impedance ..... 1  $\Omega$   
Maximum output drive current .....  $\pm 5$  mA  
Overdrive protection .....  $\pm 25$  V  
Maximum overdrive current ..... 20 mA  
Power-on state .....  $\pm 1$  mV  
Output FIFO size ..... 8191 samples shared  
                      among channels used  
Data transfer ..... USB signal stream,  
                      programmed I/O  
AO waveform modes ..... Non-periodic waveform,  
                      periodic waveform  
                      regeneration from  
                      onboard FIFO, periodic  
                      waveform regeneration  
                      from host buffer  
                      including dynamic update  
Slew rate ..... 20 V/ $\mu$ s

## AI Absolute Accuracy Table

Nominal Range		Residual GainError (ppm of Reading)	Gain Tempco (ppm/ $^{\circ}$ C)	Reference Tempco (ppm/ $^{\circ}$ C)	Residual Offset Error (ppm of Range)	Offset Tempco (ppm of Range/ $^{\circ}$ C)	INL Error (ppm of Range)	Absolute Accuracy at Full Scale <sup>1</sup> ( $\mu$ V)	Sensitivity <sup>2</sup> ( $\mu$ V)
Positive Full Scale	Negative Full Scale								
10	-10	60	13	1	20	21	60	280	1,920
5	-5	70	13	1	20	21	60	140	1,010
2	-2	70	13	1	20	24	60	57	410
1	-1	80	13	1	20	27	60	32	220
0.5	-0.5	90	13	1	40	34	60	21	130
0.2	-0.2	130	13	1	80	55	60	16	74
0.1	-0.1	150	13	1	150	90	60	15	52

AbsoluteAccuracy = Reading · (GainError) + Range · (OffsetError) + NoiseUncertainty

GainError = ResidualA(GainError + GainTempco · (TempChangeFromLastInternalCal) + ReferenceTempco · (TempChangeFromLastExternalCal))

OffsetError = ResidualA(OffsetError + OffsetTempco · (TempChangeFromLastInternalCal) + INL\_Error

$$\text{NoiseUncertainty} = \frac{\text{RandomNoise} \cdot 3}{\sqrt{100}} \quad \text{For a coverage factor of } 3 \sigma \text{ and averaging 100 points.}$$

<sup>1</sup> Absolute accuracy at full scale on the analog input channels is determined using the following assumptions:

TempChangeFromLastExternalCal = 10 °C

TempChangeFromLastInternalCal = 1 °C

number\_of\_readings = 100

CoverageFactor =  $3 \sigma$

For example, on the 10 V range, the absolute accuracy at full scale is as follows:

GainError = 60 ppm + 13 ppm · 1 + 1 ppm · 10

OffsetError = 20 ppm + 21 ppm · 1 + 60 ppm

$$\text{NoiseUncertainty} = \frac{280 \mu\text{V} \cdot 3}{\sqrt{100}} \quad \text{NoiseUncertainty} = 84 \mu\text{V}$$

AbsoluteAccuracy = 10 V · (GainError) + 10 V · (OffsetError) + NoiseUncertainty    AbsoluteAccuracy = 1920  $\mu$ V

<sup>2</sup> Sensitivity is the smallest voltage change that can be detected. It is a function of noise.

Accuracies listed are valid for up to one year from the device external calibration.

## AO Absolute Accuracy (No Load) Table

Nominal Range		Residual Gain Error (ppm of Reading)	Gain Tempco (ppm/°C)	Reference Tempco	Residual Offset Error (ppm of Range)	Offset Tempco (ppm of Range/°C)	INL Error (ppm of Range)	Absolute Accuracy at Full Scale <sup>1</sup> (µV)
Positive Full Scale	Negative Full Scale							
10	-10	75	17	1	40	2	64	2,080
5	-5	85	8	1	40	2	64	1,045

<sup>1</sup> Absolute Accuracy at Full Scale is valid immediately following internal calibration and assumes the device is operating within 10 °C of the last external calibration. Accuracies listed are valid for up to one year from the device external calibration.

AbsoluteAccuracy = OutputValue · (GainError) + Range · (OffsetError)  
 GainError = ResidualGainError + GainTempco · (TempChangeFromLastInternalCal) + ReferenceTempco · (TempChangeFromLastExternalCal)  
 OffsetError = ResidualOffsetError + AOOFFSETTempco · (TempChangeFromLastInternalCal) + INL\_Error

## Digital I/O and PFI

Number of channels.....	24 DIO (Port 0), 15 PFI (Ports 1 and 2)
Direction control.....	Each line individually programmable as input or output
Pull-down resistor.....	50 kΩ typ, 20 kΩ min
Input voltage protection.....	±20 V on up to two pins



**Note** Stresses beyond those listed under *Input voltage protection* may cause permanent damage to the device.

## DIO/PFI Recommended Operation Conditions

Level	Min	Max
Input high voltage ( $V_{IH}$ )	2.2 V	5.25 V
Input low voltage ( $V_{IL}$ )	0 V	0.8 V
Output high current ( $I_{OH}$ )		
P0.<0..23>	—	-24 mA
PFI <0..14>	—	-16 mA
Output low current ( $I_{OL}$ )		
P0.<0..23>	—	24 mA
PFI <0..14>	—	16 mA

## DIO/PFI Electrical Characteristics

Level	Min	Max
Positive-going threshold ( $VT_+$ )	—	2.2 V
Negative-going threshold ( $VT_-$ )	0.8 V	—
Delta VT hysteresis ( $VT_+ - VT_-$ )	0.2 V	—
$I_{IL}$ input low current ( $V_{in} = 0$ V)	—	-10 µA
$I_{IH}$ input high current ( $V_{in} = 5$ V)	—	250 µA

## PFI / Port 1 / Port 2 Functionality

Functionality .....	Static digital input, static digital output, timing input, timing output
Debounce filter settings .....	125 ns, 6.425 µs, 2.56 ms, disable; high and low transitions; selectable per input

## General Purpose Counter/Timers

Number of counter/timers .....	2
Resolution .....	32 bits
Counter measurements.....	Edge counting, pulse, semi period, period, two-edge separation
Position measurements .....	X1, X2, X4 quadrature encoding with Channel Z reloading; two-pulse encoding
Output applications .....	Pulse, pulse train with dynamic updates, frequency division, equivalent time sampling
Internal base clocks.....	80 MHz, 20 MHz, 0.1 MHz
External base clock frequency .....	0 MHz to 20 MHz
Base clock accuracy .....	50 ppm
Maximum frequency.....	1 MHz
Inputs .....	Gate, Source, HW_Arm, Aux, A, B, Z, Up_Down
Default Routing	
CTR0_SOURCE .....	PFI8
CTR0_GATE.....	PFI9
CTR0_OUT.....	PFI12
CTR1_SOURCE .....	PFI3
CTR1_GATE.....	PFI4
CTR1_OUT.....	PFI13
FIFO.....	2 samples
Data transfers .....	USB signal stream, programmed I/O

## Digital Frequency Generator

Number of channels .....	1
Base clocks .....	10 MHz, 100 kHz
Divisors.....	1 to 16
Maximum frequency.....	1 MHz
Base clock accuracy.....	50 ppm
Default output line .....	PFI 14 / FREQ_OUT

## External Digital Triggers

Source.....	TRIG BNC or any PFI
Polarity .....	Software selectable for most signals
Analog input function.....	Start trigger, reference trigger, pause trigger, sample clock, convert clock, sample clock timebase
Analog output function.....	Start trigger, pause trigger, sample clock, sample clock timebase
Counter/timer function .....	Gate, Source, HW_Arm, Aux, A, B, Z, Up_Down

## DMM

Isolated functions .....	DC voltage, AC voltage, DC current, AC current, resistance, diode
Isolation level.....	60 VDC / 20 V <sub>rms</sub> , Installation Category I
Connectivity.....	Banana jacks
Resolution .....	5.5 digits
Input impedance.....	11 MΩ
Input coupling .....	DC (DC voltage, DC current, resistance, diode) AC (AC voltage, AC current)
Non-isolated functions .....	Capacitance, inductance
Connectivity .....	Prototyping board terminals

## Voltage Measurement

DC Ranges.....	100 mV, 1 V, 10 V, 60 V
AC Ranges.....	200 mV <sub>rms</sub> , 2 V <sub>rms</sub> , 20 V <sub>rms</sub>
Input frequency range	
(AC voltage).....	40 Hz to 20 kHz

**DC Voltage Measurement Accuracy**  
 $\pm(\text{ppm or reading} + \text{ppm of range})$

Range	1 Year (Tcal $\pm 5^\circ\text{C}$ )	Tempco/ $^\circ\text{C}$ (15 to 35 $^\circ\text{C}$ )
100 mV	225 +280	33 + 50
1 V	225 + 60	33 + 5
10 V	225 + 40	33 + 0.5
60 V	1250 + 150	125 + 7

**AC Voltage Measurement Accuracy**  
 $\pm(\% \text{ of reading} + \% \text{ of range})$

Range (rms)	1 Year (Tcal $\pm 5^\circ\text{C}$ )	Tempco/ $^\circ\text{C}$ (15 to 35 $^\circ\text{C}$ )
200 mV	0.3 + 0.05	0.015 + 0.003
2 V		
20 V		

**Current Measurement**

DC range.....2 A

AC ranges .....500 mA<sub>rms</sub>, 2 A<sub>rms</sub>

Shunt resistance.....0.1  $\Omega$

Voltage burden .....<0.6 V

Input frequency range

(AC current) .....40 Hz to 5 kHz

Input protection .....F 3.15 A 250 V,  
 Fast-acting  
 user-replaceable fuse

**DC Current Measurement Accuracy**  
 $\pm(\text{ppm of reading} + \text{ppm of range})$

Range	1 Year (Tcal $\pm 5^\circ\text{C}$ )	Tempco/ $^\circ\text{C}$ (15 to 35 $^\circ\text{C}$ )
2 A	1350 + 180	85 + 2.5

**AC Current Measurement Accuracy**  
 $\pm(\% \text{ of reading} + \% \text{ of range})$

Range (rms)	1 Year (Tcal $\pm 5^\circ\text{C}$ )	Tempco/ $^\circ\text{C}$ (15 to 35 $^\circ\text{C}$ )
500 mA	0.5 + 0.07	0.025 + 0.003
2 A		

## Resistance Measurement

Ranges ..... 100  $\Omega$ , 1 k $\Omega$ , 10 k $\Omega$ ,  
100 k $\Omega$ , 1 M $\Omega$ , 100 M $\Omega$

## Resistance Measurement Accuracy $\pm$ (ppm of Reading + ppm of Range)

Range	Test Current	Max Test Voltage	1 Year (Tcal $\pm$ 5 °C)	Tempco/°C (15 to 35 °C)
100 $\Omega$	1 mA	100 mV	450 + 310	70 + 55
1 k $\Omega$	1 mA	1 V	450 + 100	70 + 12
10 k $\Omega$	100 $\mu$ A	1 V	450 + 100	70 + 12
100 k $\Omega$	10 $\mu$ A	1 V	450 + 100	70 + 12
1 M $\Omega$	5 $\mu$ A	5 V	450 + 100	70 + 8
100 M $\Omega$	500 nA	5 V	8000 + 75	400 + 4

## Capacitance Measurement

Range ..... 50 pF to 500  $\mu$ F

Accuracy ..... 1%

Test voltage ..... 1 V<sub>pk</sub>

Test Frequency

50 pF to 500 pF ..... 10 kHz

500 pF to 5 nF ..... 1 kHz

5 nF to 50 nF ..... 1 kHz

50 nF to 1  $\mu$ F ..... 1 kHz

1  $\mu$ F to 500  $\mu$ F ..... 100 Hz

## Inductance Measurement

Range ..... 100  $\mu$ H to 100 mH

Accuracy ..... 1%

Test voltage

100  $\mu$ H to 1 mH ..... 0.5 V<sub>pk</sub>

1 mH to 10 mH ..... 0.5 V<sub>pk</sub>

10 mH to 100 mH ..... 1 V<sub>pk</sub>

Test frequency

100  $\mu$ H to 1 mH ..... 10 kHz

1 mH to 10 mH ..... 1 kHz

10 mH to 100 mH ..... 1 kHz

## Diode Measurement<sup>1</sup>

Ranges ..... 1 V, 10 V

Nominal test current ..... 1 mA (1 V range)  
100  $\mu$ A (10 V range)

## Function Generator

Channels ..... 1

Output waveform type ..... Sine, square, triangle

Frequency range ..... 0.186 Hz to 5 MHz (sine)  
0.186 Hz to 1 MHz  
(square and triangle)

Frequency resolution ..... 0.186 Hz

DDS resolution ..... 10 bits

Waveform amplitude range ..... 10 V<sub>p-p</sub>

Waveform amplitude resolution ..... 10 bits

Waveform amplitude accuracy ..... 1%  $\pm$  15 mV

Waveform offset range .....  $\pm$  5 V

Waveform offset resolution ..... 10 bits

Waveform offset accuracy ..... 1%  $\pm$  15 mV

Duty cycle range ..... 0 to 100%

Duty cycle resolution ..... 10 bits

Duty cycle accuracy ..... 1%

Output impedance ..... 50  $\Omega$

<sup>1</sup> The Two-Wire Current Voltage Analyzer SFP is the recommended instrument for diode measurement.

Maximum output current.....	100 mA
Sine total harmonic distortion (THD).....	-50 dB max @ 1 MHz -40 dB max @ 5 MHz
Sine Flatness.....	-0.5 dB to 3 MHz -3 dB to 5 MHz

## Modulation

Inputs .....	2 (AM and FM)
Modulation input range .....	±10 V
Modulation factor	
AM .....	10%/V
FM .....	20%/V

## Oscilloscope

Channels .....	2
Sampling mode	
NI ELVIS II .....	Scanned
NI ELVIS II+.....	Simultaneous
Input coupling	
NI ELVIS II .....	AC, DC
NI ELVIS II+.....	AC, DC, GND
Input impedance	
NI ELVIS II .....	1 MΩ    25 pF
NI ELVIS II+.....	1 MΩ    21 pF
Bandwidth (-3 dB)	
NI ELVIS II .....	1.7 MHz
NI ELVIS II+.....	35 MHz (40 mV <sub>p-p</sub> ) 50 MHz (all other ranges)

Optional noise filter	
NI ELVIS II .....	None
NI ELVIS II+.....	20 MHz
AC coupling cutoff frequency (-3 dB)	
NI ELVIS II .....	10 Hz
NI ELVIS II+.....	12 Hz
Resolution	
NI ELVIS II .....	16 bits
NI ELVIS II+.....	8 bits

Maximum sample rate	
NI ELVIS II	
Single channel .....	1.25 MS/s
Two channels.....	500 kS/s
NI ELVIS II+.....	100 MS/s

Minimum sample rate

NI ELVIS II.....	0.00465 S/s
NI ELVIS II+.....	1.526 kS/s
Timebase accuracy.....	50 ppm
Waveform memory depth	
NI ELVIS II.....	Streaming to host
NI ELVIS II+.....	16384 samples per channel

## Triggering

### BNC TRIG Input

Input impedance.....	1 MΩ
V <sub>IH</sub> min .....	2.4 V
V <sub>IL</sub> max .....	400 mV
Minimum pulse width.....	20 ns

### NI ELVIS II

Refer to the [Analog Input](#) section.

### NI ELVIS II+

Type	Source
Edge, Hysteresis	CH 0, CH 1
Digital	BNC TRIG Input (PFI 15), FGEN SYNC
Immediate	—

## DC Accuracy

### NI ELVIS II

Range	Gain Error (% of reading)	Offset Error (% of range)
(±) 10 V, 5 V	0.15	0.1
(±) 2 V	0.15	0.15
(±) 1 V, 0.5 V	0.1	0.15
(±) 0.2 V	0.1	0.5
(±) 0.1 V	0.2	0.5

## NI ELVIS II+

Range (V <sub>pk-pk</sub> )	Programmable Vertical Offset		Typical Noise (V <sub>rms</sub> )
	Range (V)	Offset Accuracy	
0.04	±0.4	±2 mV	0.00022
0.1	±0.4	±10 mV	0.00035
0.2	±0.4	±10 mV	0.0007
0.4	±0.4	±10 mV	0.0014
1	±4	±100 mV	0.0035
2	±4	±100 mV	0.007
4	±4	±100 mV	0.014
10	±25	±625 mV	0.035
20	±20	±625 mV	0.07
40	±10	±625 mV	0.14

Accuracy ..... ±(2% of Input +  
1% of Full Scale  
Range + 300 µV)



**Note** Accuracy is calculated with the programmable offset = 0 V and at ±5 °C from the self-calibration temperature.

DC drift ..... ±(0.033% of Input +  
0.06% of Full Scale  
Range + 40 µV) per °C

## Dynamic Signal Analyzer

Frequency resolution ..... Software controllable  
(200, 400, 800, 1600,  
3200 lines)

Accuracy

NI ELVIS II ..... Refer to the [Analog Input](#)  
section.  
  
NI ELVIS II+  
(using scope channels) ..... Refer to the [Oscilloscope](#)  
section.

Frequency range

NI ELVIS II ..... Up to 625 kHz

NI ELVIS II+  
(using scope channels) ..... Up to 50 MHz

## Bode Analyzer

Amplitude accuracy

NI ELVIS II ..... Refer to the [Analog Input](#)  
section.

NI ELVIS II+  
(using scope channels) ..... Refer to the [Oscilloscope](#)  
section.

Frequency range

NI ELVIS II ..... 1 Hz to 200 kHz

NI ELVIS II+  
(using scope channels) ..... 1 Hz to 5 MHz

## Two-Wire Current-Voltage Analyzer

Current range ..... ±40 mA

Voltage sweep range ..... ±10 V

## Three-Wire Current-Voltage Analyzer

Supported devices ..... NPN and PNP transistors

Minimum base current step ..... 0.48 µA

Maximum collector current ..... ±40 mA

Maximum collector voltage ..... ±10 V

## Impedance Analyzer

Excitation frequency ..... 1 Hz to 35 kHz

Resistance measurement range ..... 5 Ω to 3 MΩ

Capacitance measurement range ..... Refer to the [DMM](#),  
[Capacitance](#)  
[Measurement](#) section.

Inductance measurement range ..... Refer to the [DMM](#),  
[Inductance Measurement](#)  
section.

## **Power Supplies<sup>1</sup>**

### **+15 V Supply**

Output voltage (no load).....	+15 V $\pm$ 5%
Maximum output current.....	500 mA
Ripple and noise .....	1% peak-to-peak max.
Load regulation.....	5%
Short circuit protection.....	Resettable circuit breaker

### **-15 V Supply**

Output voltage (no load).....	-15 V $\pm$ 5%
Maximum output current.....	500 mA
Ripple and noise .....	1% peak-to-peak max.
Load regulation.....	5%
Short circuit protection.....	Resettable circuit breaker

### **+5 V Supply**

Output voltage (no load).....	+5 V $\pm$ 5%
Maximum output current.....	2 A
Ripple and noise .....	1% peak-to-peak max.
Load regulation.....	5%
Short circuit protection.....	Resettable circuit breaker

### **Positive Variable Supply**

Output voltage <sup>2</sup> .....	0 to +12 V
Voltage setpoint resolution.....	10 bits
Voltage accuracy (no load).....	100 mV
Maximum output current.....	500 mA
Ripple and noise .....	25 mV
Short circuit protection.....	Self-resetting current limiter

### **Negative Variable Supply**

Output voltage.....	0 to -12 V
Voltage setpoint resolution .....	10 bits
Voltage accuracy (no load) .....	100 mV
Maximum output current .....	500 mA
Ripple and noise.....	25 mV
Short circuit protection .....	Self-resetting current limiter

### **Calibration**

Recommended warm-up time .....	30 minutes
Calibration interval .....	1 year

### **Communication**

Bus interface .....	USB 2.0 Hi-Speed
USB signal stream .....	4 streams; can be used for analog input, analog output, and counter/timers

### **Physical**

Dimensions .....	34.3 $\times$ 28.0 $\times$ 7.6 cm (14.5 $\times$ 11.0 $\times$ 3 in.)
Weight.....	1.9 kg (4.2 lb)

### **Environmental**

Operating temperature .....	10 to 35 °C
Storage temperature .....	-20 to 70 °C
Humidity .....	10 to 90% relative humidity, noncondensing
Maximum altitude.....	2,000 m
Pollution Degree (indoor use only).....	2

<sup>1</sup> Total output power of all DC and variable power supplies is 30 W.

<sup>2</sup> At least 1 mA of load current is required for voltage setpoints lower than +250 mV.

## Safety

This product meets the requirements of the following standards of safety for electrical equipment for measurement, control, and laboratory use:

- IEC 61010-1, EN 61010-1
- UL 61010-1, CSA 61010-1



**Note** For UL and other safety certifications, refer to the product label or the *Online Product Certification* section.

## Electromagnetic Compatibility

This product meets the requirements of the following EMC standards for electrical equipment for measurement, control, and laboratory use:

- EN 61326 (IEC 61326): Class A emissions; Basic immunity
- EN 55011 (CISPR 11): Group 1, Class A emissions
- AS/NZS CISPR 11: Group 1, Class A emissions
- FCC 47 CFR Part 15B: Class A emissions
- ICES-001: Class A emissions



**Note** For the standards applied to assess the EMC of this product, refer to the *Online Product Certification* section.



**Note** For EMC compliance, operate this product according to the documentation.

## CE Compliance

This product meets the essential requirements of applicable European Directives as follows:

- 2006/95/EC; Low-Voltage Directive (safety)
- 2004/108/EC; Electromagnetic Compatibility Directive (EMC)

## Online Product Certification

Refer to the product Declaration of Conformity (DoC) for additional regulatory compliance information. To obtain product certifications and the DoC for this product, visit [ni.com/certification](http://ni.com/certification), search by model number or product line, and click the appropriate link in the Certification column.

## Environmental Management

NI is committed to designing and manufacturing products in an environmentally responsible manner. NI recognizes that eliminating certain hazardous substances from our products is beneficial to the environment and to NI customers.

For additional environmental information, refer to the *NI and the Environment* Web page at [ni.com/environment](http://ni.com/environment). This page contains the environmental regulations and directives with which NI complies, as well as other environmental information not included in this document.

## Waste Electrical and Electronic Equipment (WEEE)



**EU Customers** At the end of the life cycle, all products *must* be sent to a WEEE recycling center. For more information about WEEE recycling centers and National Instruments WEEE initiatives, visit [ni.com/environment/weee](http://ni.com/environment/weee).

## 电子信息产品污染控制管理办法（中国 RoHS）



**中国客户** National Instruments 符合中国电子信息产品中限制使用某些有害物质指令 (RoHS)。关于 National Instruments 中国 RoHS 合规性信息, 请登录 [ni.com/environment/rohs\\_china](http://ni.com/environment/rohs_china)。  
(For information about China RoHS compliance, go to [ni.com/environment/rohs\\_china](http://ni.com/environment/rohs_china).)

National Instruments, NI, ni.com, and LabVIEW are trademarks of National Instruments Corporation. Refer to the *Terms of Use* section on [ni.com/legal](http://ni.com/legal) for more information about National Instruments trademarks. Other product and company names mentioned herein are trademarks or trade names of their respective companies. For patents covering National Instruments products/technology, refer to the appropriate location: **Help>Patents** in your software, the *patents.txt* file on your media, or the *National Instruments Patent Notice* at [ni.com/patents](http://ni.com/patents).