


PM6306 PROGRAMMABLE AUTOMATIC RCL METER

DC - 1MHz


Operating Card

4822 872 10144
960508




FLUKE®

Auto Mode Decision Diagram



* For test signal voltages ≤ 0.25 V, the decision criterion is $Q = 200$, $D = 0.05$, or $Q = 0.05$, $D = 200$


Measurement Ranges and Accuracy, Level 1 V



- Test signal frequency 50 Hz to 1 MHz or DC (option).
- For SMD components use the PM 9542SMD, SMD ADAPTER or the PM 9540/TWE, SMD TWEEZERS.
- For larger components use the PM 9542A, RCL Adapter.
- For in-circuit measurement of components use the PM 9541A 4-WIRE TEST CABLE (Kelvin Clips) or the PM 9540/TWE, SMD TWEEZERS.
- Discharge capacitors before connecting.
- The middle segments of the upper digits light up when the component exceeds the measurement range:
 - $R > 200$ MΩ at AC, $R > 50$ MΩ at DC
 - $L > 637$ kH at 50 Hz, > 31.8 H at 1 MHz
 - $C > 32$ F at 50 Hz, > 160 μF at 1 MHz.
- Asterisk lights up if the component is outside the basic accuracy of the instrument. Select appropriate test signal frequency.
- ZERO TRIM** compensates:
 - Contact and line resistors (up to 10 Ω in short-circuit).
 - Stray capacitances in open-circuit.


www.valuetronics.com

Auto Mode Decision Diagram



* For test signal voltages ≤ 0.25 V, the decision criterion is $Q = 200$, $D = 0.05$, or $Q = 0.05$, $D = 200$

Measurement Ranges and Accuracy, Level 1 V



- Test signal frequency 50 Hz to 1 MHz or DC (option).
- For SMD components use the PM 9542SMD, SMD ADAPTER or the PM 9540/TWE, SMD TWEEZERS.
- For larger components use the PM 9542A, RCL Adapter.
- For in-circuit measurement of components use the PM 9541A 4-WIRE TEST CABLE (Kelvin Clips) or the PM 9540/TWE, SMD TWEEZERS.
- Discharge capacitors before connecting.
- The middle segments of the upper digits light up when the component exceeds the measurement range:
 - $R > 200$ MΩ at AC, $R > 50$ MΩ at DC
 - $L > 637$ kH at 50 Hz, > 31.8 H at 1 MHz
 - $C > 32$ F at 50 Hz, > 160 μF at 1 MHz.
- Asterisk lights up if the component is outside the basic accuracy of the instrument. Select appropriate test signal frequency.
- ZERO TRIM** compensates:
 - Contact and line resistors (up to 10 Ω in short-circuit).
 - Stray capacitances in open-circuit.