



11678A Low-Pass Filter Kit

Data Sheet

Product Specifications

Frequency Range (low-pass filters, cutoff frequency f_c):

Agilent 11688A: 2.8 GHz

Agilent 11689A: 4.4 GHz

Agilent 11684A: 6.8 GHz

Agilent 11685A: 9.5 GHz

Agilent 11686A: 13.0 GHz

Insertion Loss: <1.1 dB at 0.95 f_c

Rejection (at 1.25 f_c): Greater than 40 dB

Impedance: 50 ohms normal

Connectors: Type-N female and male

Net Weight: 0.44 kg (1 lb)

Shipping Weight: 1.2 kg (2.9 lb)



Agilent Technologies