

# R&S<sup>®</sup>SMCVB-KV12

## DRM+ Waveforms

### User Manual



1179277702  
Version 01

**ROHDE & SCHWARZ**  
Make ideas real



This document describes the following software options:

- R&S®SMCVB-KV12 DRM+ Waveforms (1434.5405.xx)

© 2020 Rohde & Schwarz GmbH & Co. KG

Mühlhofstr. 15, 81671 München, Germany

Phone: +49 89 41 29 - 0

Email: [info@rohde-schwarz.com](mailto:info@rohde-schwarz.com)

Internet: [www.rohde-schwarz.com](http://www.rohde-schwarz.com)

Subject to change – data without tolerance limits is not binding.

R&S® is a registered trademark of Rohde & Schwarz GmbH & Co. KG.

Trade names are trademarks of the owners.

1179.2777.02 | Version 01 | R&S®SMCVB-KV12

The following abbreviations are used throughout this manual: R&S®SMCV100B is abbreviated as R&S SMCV100B.

# Contents

<b>1</b>	<b>Welcome to the R&amp;S SMCVB-KV12 Option.....</b>	<b>5</b>
<b>1.1</b>	<b>Key Features.....</b>	<b>5</b>
<b>1.2</b>	<b>Installation.....</b>	<b>5</b>
<b>1.3</b>	<b>Documentation Overview.....</b>	<b>5</b>
1.3.1	Getting Started Manual.....	5
1.3.2	User Manuals and Help.....	5
1.3.3	Service Manual.....	6
1.3.4	Instrument Security Procedures.....	6
1.3.5	Printed Safety Instructions.....	6
1.3.6	Data Sheets and Brochures.....	6
1.3.7	Release Notes and Open Source Acknowledgment (OSA).....	7
1.3.8	Application Notes, Application Cards, White Papers, etc.....	7
<b>2</b>	<b>Available Waveform Files.....</b>	<b>8</b>
<b>2.1</b>	<b>General Settings and Features.....</b>	<b>8</b>
<b>2.2</b>	<b>Naming Conventions.....</b>	<b>8</b>
<b>2.3</b>	<b>DRM Settings.....</b>	<b>9</b>
2.3.1	4QAM MSC Mapping.....	9
2.3.1.1	MSC_4QAM_MSC_LPP_0_MSC_HPP_0_SDC_1.wv.....	9
2.3.1.2	MSC_4QAM_MSC_LPP_1_MSC_HPP_1_SDC_1.wv.....	10
2.3.1.3	MSC_4QAM_MSC_LPP_1_MSC_HPP_1_SDC_0.wv.....	11
2.3.1.4	MSC_4QAM_MSC_LPP_2_MSC_HPP_1_SDC_1.wv.....	12
2.3.1.5	MSC_4QAM_MSC_LPP_2_MSC_HPP_2_SDC_1.wv.....	14
2.3.1.6	MSC_4QAM_MSC_LPP_2_MSC_HPP_3_SDC_1.wv.....	15
2.3.1.7	MSC_4QAM_MSC_LPP_2_MSC_HPP_3_SDC_0.wv.....	16
2.3.1.8	MSC_4QAM_MSC_LPP_3_MSC_HPP_3_SDC_0.wv.....	17
2.3.2	16QAM MSC Mapping.....	19
2.3.2.1	MSC_16QAM_MSC_LPP_0_MSC_HPP_0_SDC_1.wv.....	19
2.3.2.2	MSC_16QAM_MSC_LPP_1_MSC_HPP_1_SDC_1.wv.....	20
2.3.2.3	MSC_16QAM_MSC_LPP_1_MSC_HPP_1_SDC_0.wv.....	21
2.3.2.4	MSC_16QAM_MSC_LPP_2_MSC_HPP_1_SDC_1.wv.....	22
2.3.2.5	MSC_16QAM_MSC_LPP_2_MSC_HPP_2_SDC_1.wv.....	23

2.3.2.6	MSC_16QAM_MSC_LPP_2_MSC_HPP_3_SDC_1.wv.....	25
2.3.2.7	MSC_16QAM_MSC_LPP_2_MSC_HPP_3_SDC_0.wv.....	26
2.3.2.8	MSC_16QAM_MSC_LPP_3_MSC_HPP_3_SDC_0.wv.....	27
<b>2.4</b>	<b>DRM Services.....</b>	<b>28</b>
2.4.1	Services_1_AAC.wv.....	29
2.4.2	Services_2_HE-AAC_xHE-AAC.wv.....	30
2.4.3	Services_2_HE-AAC_AAC.wv.....	31
2.4.4	Services_3_HE-AAC_AAC_PRBS.wv.....	32
2.4.5	Services_3_HE-AAC_HE-AAC_PRBS.wv.....	33
2.4.6	Services_4_xHE-AAC_xHE-AAC_xHE-AAC_xHE-AAC.wv.....	34
<b>2.5</b>	<b>EN 303 345 DRM Testing.....</b>	<b>35</b>
2.5.1	VHF_wanted.wv.....	35
2.5.2	VHF_unwanted.wv.....	36
	<b>Index.....</b>	<b>38</b>

# 1 Welcome to the R&S SMCVB-KV12 Option

The R&S SMCVB-KV12 is a waveform library that provides waveform files in accordance with the DRM+ digital standard.

This user manual contains a reference description of the functionality that the waveform library provides. All functions not discussed in this manual are described in the R&S SMCV100B user manual. The latest version is available at:

[www.rohde-schwarz.com/manual/SMCV100B](http://www.rohde-schwarz.com/manual/SMCV100B)

## 1.1 Key Features

The R&S SMCVB-KV12 features:

- Numerous waveform files in accordance with DRM+ digital standard
- Efficient use with dedicated waveforms

## 1.2 Installation

You can find detailed installation instructions in the supplement document of the R&S SMCV100B user manual and in the R&S SMCV100B user manual describing firmware versions later than FW 4.70.176.xx of the R&S SMCV100B.

## 1.3 Documentation Overview

This section provides an overview of the R&S SMCV100B user documentation. Unless specified otherwise, you find the documents on the R&S SMCV100B product page at:

[www.rohde-schwarz.com/manual/smcv100b](http://www.rohde-schwarz.com/manual/smcv100b)

### 1.3.1 Getting Started Manual

Introduces the R&S SMCV100B and describes how to set up and start working with the product. Includes basic operations, typical measurement examples, and general information, e.g. safety instructions, etc. A printed version is delivered with the instrument.

### 1.3.2 User Manuals and Help

Separate manuals for the base unit and the software options are provided for download:

- Base unit manual

Contains the description of all instrument modes and functions. It also provides an introduction to remote control, a complete description of the remote control commands with programming examples, and information on maintenance, instrument interfaces and error messages. Includes the contents of the getting started manual.

- **Software option manual**  
Contains the description of the specific functions of an option. Basic information on operating the R&S SMCV100B is not included.

The contents of the user manuals are available as help in the R&S SMCV100B. The help offers quick, context-sensitive access to the complete information for the base unit and the software options.

All user manuals are also available for download or for immediate display on the Internet.

### 1.3.3 Service Manual

Describes the performance test for checking compliance with rated specifications, firmware update, troubleshooting, adjustments, installing options and maintenance.

The service manual is available for registered users on the global Rohde & Schwarz information system (GLORIS):

<https://gloris.rohde-schwarz.com>

### 1.3.4 Instrument Security Procedures

Deals with security issues when working with the R&S SMCV100B in secure areas. It is available for download on the Internet.

### 1.3.5 Printed Safety Instructions

Provides safety information in many languages. The printed document is delivered with the product.

### 1.3.6 Data Sheets and Brochures

The data sheet contains the technical specifications of the R&S SMCV100B. It also lists the options and their order numbers and optional accessories.

The brochure provides an overview of the instrument and deals with the specific characteristics.

See [www.rohde-schwarz.com/brochure-datasheet/smcv100b](http://www.rohde-schwarz.com/brochure-datasheet/smcv100b)

### 1.3.7 Release Notes and Open Source Acknowledgment (OSA)

The release notes list new features, improvements and known issues of the current firmware version, and describe the firmware installation.

The open-source acknowledgment document provides verbatim license texts of the used open source software.

See [www.rohde-schwarz.com/firmware/smcv100b](http://www.rohde-schwarz.com/firmware/smcv100b)

### 1.3.8 Application Notes, Application Cards, White Papers, etc.

These documents deal with special applications or background information on particular topics.

See [www.rohde-schwarz.com/application/smcv100b](http://www.rohde-schwarz.com/application/smcv100b)

## 2 Available Waveform Files

### 2.1 General Settings and Features

All files have general features and settings as follows:

- DRM Mode E (DRM+)
- Sample rate 192 kHz
- Bandwidth 100 kHz
- Filter bandwidth 2x 76.8 kHz
- File length approx. 500 MB
- Play time per file approx. 10 minutes
- Included PRPS services have the polynomial  $G_{23}(x)=x^{23} + x^{18} + 1$ , register contents are initially all set to binary 1.

### 2.2 Naming Conventions

#### DRM setting files (chapter 2.3)

The file name consists of:

- MSC mapping type
- MSC lower protection level
- MSC higher protection level
- SDC protection level

Example: `MSC_4QAM_MSC_LPP_0_MSC_HPP_0_SDC_1.wv`

This file has the following characteristics:

- MSC mapping type: 4QAM
- MSC lower protection level (MSC\_LPP): 0
- MSC higher protection level (MSC\_HPP): 0
- SDC protection level (SDC): 1

#### DRM service files (chapter 2.3)

The file name consists of:

- Services
- Number of services
- Audio coding of each service

Example: `Services_3_HE-AAC_HE-AAC_PRBS.wv`

This file has the following characteristics:

- Contains 3 services
- Audio coding: service 0: HE-AAC; service 1: HE-AAC; service 2: data PRBS

### EN 303 345 DRM testing files (chapter 2.5)

The file name consists of:

- Frequency band
- Wanted/unwanted signal

Example: VHF\_wanted.wv

In this standard, there are three different frequency bands defined. Only the VHF band uses robustness mode E. The other frequency bands use robustness mode B and are excluded from this library. These files are part of the waveform library R&S SMCVB-KV11 DRM Waveforms (1434.5370.xx).

## 2.3 DRM Settings

### 2.3.1 4QAM MSC Mapping

Describes the files with 4QAM MSC mapping and different protection levels.

#### 2.3.1.1 MSC\_4QAM\_MSC\_LPP\_0\_MSC\_HPP\_0\_SDC\_1.wv

*Table 2-1: General settings*

Samples	125337600
Peak offset	3.12 dB
Peak/RMS	12.44 dB
Duration	10 minutes 52 seconds
MSC mapping	4QAM
MSC lower protection	0 (highest)
MSC higher protection	0 (highest)
SDC protection	1 (highest)

Service 2 and 3 are not available.

*Table 2-2: Services*

	Service 0	Service 1
Service ID	0xAFFE	0xAFFF
Language	Japanese	Korean

<b>Service label</b>	HE-AAC	Data PRBS
<b>Service content</b>	Audio HE-AAC 16.32 kb/s HPP 43 bytes 24 kHz Param. stereo + SBR	PRBS 20.88 kb/s Synchronized Low protected: 226 bytes High protected: 35 bytes
<b>Program type</b>	Varied	
<b>Links to AFS1</b>		
<b>Service</b>	eFM+RDS, 0xD001	
<b>Schedule</b>	None	
<b>Content</b>	Equal	
<b>Frequency</b>	96.6 MHz	
<b>Local Information</b>		
<b>Country</b>	Germany	
<b>Language of audience</b>	English	
<b>Text</b>		
<b>Text headline</b>	Text Message Service 0	
<b>Text content</b>	Rohde & Schwarz GmbH & Co. KG Munich, Germany Waveform Library DRM Mode E	
<b>Text transmit</b>	4 times	

### 2.3.1.2 MSC\_4QAM\_MSC\_LPP\_1\_MSC\_HPP\_1\_SDC\_1.wv

Table 2-3: General settings

<b>Samples</b>	126028800
<b>Peak offset</b>	2.83 dB
<b>Peak/RMS</b>	12.75 dB
<b>Duration</b>	10 minutes 56 seconds
<b>MSC mapping</b>	4QAM
<b>MSC lower protection</b>	1 (high)
<b>MSC higher protection</b>	1 (high)
<b>SDC protection</b>	1 (highest)

Service 2 and 3 are not available.

Table 2-4: services

	Service 0	Service 1
Service ID	0xAFFA	0xAFFF
Language	German	English
Service label	Service 0 xHE	Data PRBS
Service content	Audio xHE-AAC 32.08 kb/s No HPP 38.4 kHz Stereo no SBR	Data PRBS 17.6 kb/s Synchronized Low protected: 220 bytes High protected: 0 bytes
Program type	Varied	
<b>Links to AFS1</b>		
Service	eFM+RDS, 0xD001	-
Schedule	None	-
Content	Equal	-
Frequency	96.6 MHz	-
<b>Local Information</b>		
Country	Germany	
Language of audience	English	
<b>Text</b>		
Text headline	Text Message Service 0	
Text content	Rohde & Schwarz GmbH & Co. KG Munich, Germany Waveform Library DRM Mode E	
Text transmit	4 times	

### 2.3.1.3 MSC\_4QAM\_MSC\_LPP\_1\_MSC\_HPP\_1\_SDC\_0.wv

Table 2-5: General settings

Samples	125107200
Peak offset	3.84 dB
Peak/RMS	12.06 dB
Duration	10 minutes 51 seconds
MSC mapping	4QAM
MSC lower protection	1 (high)

MSC higher protection	1 (high)
SDC protection	0 (weak)

Service 3 is not available.

**Table 2-6: Services**

	Service 0	Service 1	Service 2
Service ID	0xAFFE	0xF	0xFF
Language	German	German	German
Service label	Audio 0 HE-AAC	Audio 1 HE-AAC	Audio 2 HE-AAC
Service content	Audio HE-AAC 16.32 kb/s HPP: 43 bytes 24 kHz Param. stereo + SBR	Audio HE-AAC 16.32 kb/s HPP: 43 bytes 24 kHz Param. stereo + SBR	Audio xHE-AAC 16.32 kb/s HPP 43 bytes 24 kHz Param. stereo + SBR
Program type	Pop music	Other music	Science
<b>Links to AFS1</b>			
Service	eFM+RDS, D001	eFM+RDS 0xD001	eFM (no service ID)
Schedule	None	None	None
Content	Equal	Equal	Equal
Frequency	96.6 MHz	88.9 MHz	88.9 MHz
<b>Local Information</b>			
Country	Germany	Canada	Canada
Language of audience	English	Kakota	Balinese
<b>Text</b>			
Text headline	Text Message Service 0	Text Message Service 1	Text Message Service 2
Text content	Munich, Germany Waveform Library DRM Mode E Rohde&Schwarz	DRM Mode E Waveform Library Rohde & Schwarz GmbH & Co. KG Munich, Germany	DRM Mode E Waveform Library Rohde & Schwarz Broadcast and Media Division Munich, Germany
Text transmit	4 times	6 times	4 times

#### 2.3.1.4 MSC\_4QAM\_MSC\_LPP\_2\_MSC\_HPP\_1\_SDC\_1.wv

**Table 2-7: General settings**

Samples	125107200
Peak offset	3.76 dB

<b>Peak/RMS</b>	11.79 dB
<b>Duration</b>	10 minutes 51 seconds
<b>MSC mapping</b>	4QAM
<b>MSC lower protection</b>	2 (medium)
<b>MSC higher protection</b>	1 (high)
<b>SDC protection</b>	1 (highest)

Table 2-8: Services

	<b>Service 0</b>	<b>Service 1</b>	<b>Service 2</b>	<b>Service 3</b>
<b>Service ID</b>	0xAFFE	0xF	0xFF	0xAFFF
<b>Language</b>	German	German	English	Not specified
<b>Service label</b>	Audio 0 HE-AAC	Audio 1 HE-AAC	Audio 2 HE-AAC	Data PRBS
<b>Service content</b>	Audio HE-AAC 16.32 kb/s HPP: 43 bytes 24 kHz Param. stereo + SBR	Audio HE-AAC 16.32 kb/s HPP: 43 bytes 24 kHz Param. stereo + SBR	Audio HE-AAC 16.32 kb/s HPP: 43 bytes 24 kHz Param. stereo + SBR	Data PRBS 8.48 kb/s Synchronized Low protected: 104 bytes High protected : 2 bytes
<b>Program type</b>	Pop music	Other music	Science	
<b>Links to AFS1</b>				
<b>Service</b>	eFM+RDS, D001	eFM+RDS 0xD001	eFM (no service ID)	
<b>Schedule</b>	None	None	None	
<b>Content</b>	Equal	Equal	Different	
<b>Frequency</b>	96.6 MHz	88.9 MHz	87.5 MHz	
<b>Local Information</b>				
<b>Country</b>	Germany	Canada	Canada	
<b>Language of audience</b>	English	Dakota	Balinese	
<b>Text</b>				
<b>Text headline</b>	Text Message Service 0	Text Message Service 1	Text Message Service 2	

<b>Text content</b>	Rohde & Schwarz GmbH & Co. KG Munich, Germany Waveform Library DRM Mode E	DRM Mode E Waveform Library Rohde & Schwarz GmbH & Co. KG Munich, Germany	DRM Mode E Waveform Library Rohde & Schwarz Broadcast and Media Division Munich, Germany	
<b>Text transmit</b>	4 times	6 times	5 times	

### 2.3.1.5 MSC\_4QAM\_MSC\_LPP\_2\_MSC\_HPP\_2\_SDC\_1.wv

Table 2-9: General settings

<b>Samples</b>	125337600
<b>Peak offset</b>	4.73 dB
<b>Peak/RMS</b>	11.75 dB
<b>Duration</b>	10 minutes 52 seconds
<b>MSC mapping</b>	4QAM
<b>MSC lower protection</b>	2 (medium)
<b>MSC higher protection</b>	2 (medium)
<b>SDC protection</b>	1 (highest)

Table 2-10: Services

	<b>Service 0</b>	<b>Service 1</b>	<b>Service 2</b>	<b>Service 3</b>
<b>Service ID</b>	0xAFFE	0xF	0xFF	0xAFFF
<b>Language</b>	German	German	English	Not specified
<b>Service label</b>	Audio 0 HE-AAC	Audio 1 HE-AAC	Audio 2 HE-AAC	Not specified
<b>Service content</b>	Audio HE-AAC 16.32 kb/s HPP 43 bytes 24 kHz Param. stereo +SBR	Audio HE-AAC 16.32 kb/s HPP 43 bytes 24 kHz Param. stereo +SBR	Audio HE-AAC 16.32 kb/s HPP 43 bytes 24 kHz Param. stereo + SBR	Data PRBS 10.64 kb/s Synchronized Low protected: 130 bytes High protected : 3 bytes
<b>Program type</b>	Music	Other music		
<b>Links to AFS1</b>				
<b>Service</b>	eFM+RDS, D001	eFM+RDS, D001	eFM (no service ID)	
<b>Schedule</b>	None	None	None	
<b>Content</b>	Equal	Equal	Equal	
<b>Frequency</b>	96.6 MHz	88.9 MHz	88.9 MHz	

<b>Local Information</b>				
<b>Country</b>	Germany	Canada	Canada	
<b>Language of audience</b>	English	Dakota	Balinese	
<b>Text</b>				
<b>Text headline</b>	Message Service 0	Text Message Service 1	Text Message Service 2	
<b>Text content</b>	Rohde & Schwarz GmbH & Co. KG Munich, Germany Waveform Library DRM Mode E	DRM Mode E Waveform Library Rohde & Schwarz GmbH & Co. KG Munich, Germany	DRM Mode E Waveform Library Rohde & Schwarz Broadcast and Media Division Munich, Germany	
<b>Text transmit</b>	4 times	6 times	5 times	

### 2.3.1.6 MSC\_4QAM\_MSC\_LPP\_2\_MSC\_HPP\_3\_SDC\_1.wv

Table 2-11: General settings

<b>Samples</b>	125337600
<b>Peak offset</b>	2.38 dB
<b>Peak/RMS</b>	12.82 dB
<b>Duration</b>	10 minutes 52 seconds
<b>MSC mapping</b>	4QAM
<b>MSC lower protection</b>	2 (medium)
<b>MSC higher protection</b>	3 (weak)
<b>SDC protection</b>	1 (highest)

Service 3 is not available.

Table 2-12: Services

	<b>Service 0</b>	<b>Service 1</b>	<b>Service 2</b>
<b>Service ID</b>	0xAFFE	0x422	0x423
<b>Language</b>	German	German	Not specified
<b>Service label</b>	Audio 0 HE-AAC	Label audio 1 AAC	Data PRBS
<b>Service content</b>	Audio HE-AAC 16.32 kb/s HPP: 43 bytes 24 kHz Param. stereo no SBR	Audio AAC 32.0 kb/s HPP 83 bytes 48 kHz Mono	Data PRBS 13.36 bit/s Synchronized Low protected: 163 bytes High protected: 4 bytes
<b>Program type</b>	Pop music	Serious classical	--

<b>Links to AFS1</b>			
<b>Service</b>	eFM+RDS, D001	DAB 0x422	
<b>Schedule</b>	None	None	
<b>Content</b>	Equal	Equal	
<b>Frequency</b>	96.6 MHz	5A	
<b>Local Information</b>			
<b>Country</b>	Germany	Austria	
<b>Language of audience</b>	English	Not specified	
<b>Text</b>			
<b>Text headline</b>	Text Message Service 0	Text Message Service 1	
<b>Text content</b>	Rohde & Schwarz GmbH & Co. KG Munich, Germany Waveform Library DRM Mode E	DRM Mode E Waveform Library Rohde & Schwarz GmbH & Co. KG Munich, Germany	
<b>Text transmit</b>	4 times	6 times	

### 2.3.1.7 MSC\_4QAM\_MSC\_LPP\_2\_MSC\_HPP\_3\_SDC\_0.wv

*Table 2-13: General settings*

<b>Samples</b>	125337600
<b>Peak offset</b>	3.36 dB
<b>Peak/RMS</b>	12.49 dB
<b>Duration</b>	10 minutes 52 seconds
<b>MSC mapping</b>	4QAM
<b>MSC lower protection</b>	2 (medium)
<b>MSC higher protection</b>	3 (weak)
<b>SDC protection</b>	0 (weak)

*Table 2-14: Services*

	<b>Service 0</b>	<b>Service 1</b>	<b>Service 2</b>	<b>Service 3</b>
<b>Service ID</b>	0xC1D2	0x467	0x468	0x469
<b>Language</b>	Hindi	German	German	German
<b>Service label</b>	Audio xHE-AAC	Audio xHE-AAC	Audio xHE-AAC	Data slideshow

<b>Service content</b>	Audio xHE-AAC 16.32 kb/s No HHP 32 kHz Stereo no SBR	Audio xHE-AAC 14.96 kb/s No HPP 32 kHz Stereo no SBR	Audio xHE-AAC 14.96 kb/s No HHP 24 kHz Stereo no SBR	Packed data 10.96 kb/s Low protected: 155 bytes High protected: 5 bytes MOT slideshow 10.96 kb/s
<b>Program type</b>	Science	Varied	Other music	
<b>Links to AFS1</b>				
<b>Service</b>	aFM (no Service ID)	aFM+PI 0x467	DRM+	
<b>Schedule</b>	Schedule 1	Schedule 1	Schedule 1	
<b>Content</b>	Equal	Equal	Equal	
<b>Frequency</b>	76 MHz	76 MHz	100.0 MHz	
<b>Local Information</b>				
<b>Country</b>	India	Pakistan	Afghanistan	Cameroon
<b>Language of audience</b>	Hindi	Urdu	Artificial language	Not specified
<b>Text</b>				
<b>Text headline</b>	Text Message Service 0	Text Message Service 1	Text Message Service 2	
<b>Text content</b>	Company Rohde&Schwarz Munich, Germany DRM Mode E Waveform Library	Waveform Library DRM+ ES 201 980 Rohde & Schwarz Germany, Munich	PC based DRM modulator DRM Mode E Rohde&Schwarz GmbH & Co. KG Germany, Munich	
<b>Text transmit</b>	4 times	11 times		

### 2.3.1.8 MSC\_4QAM\_MSC\_LPP\_3\_MSC\_HPP\_3\_SDC\_0.wv

Table 2-15: General settings

<b>Samples</b>	125337600
<b>Peak offset</b>	3.09 dB
<b>Peak/RMS</b>	12.60 dB
<b>Duration</b>	10 minutes 52 seconds
<b>MSC mapping</b>	4QAM
<b>MSC lower protection</b>	3 (weak)

MSC higher protection	3 (weak)
SDC protection	0 (weak)

Table 2-16: Services

	Service 0	Service 1	Service 2	Service 3
<b>Service ID</b>	0xC1D2	0x467	0x468	0x469
<b>Language</b>	Hindi	German	German	German
<b>Service label</b>	Audio0 xHE-AAC	Audio1 xHE-AAC	Audio2 HE-AAC	Data slideshow
<b>Service content</b>	Audio xHE-AAC 18.08 kb/s No HHP 32 kHz Stereo no SBR	Audio xHE-AAC 22.96 kb/s No HHP 32 kHz Stereo no SBR	Audio HE-AAC 16.32 kb/s HHP: 43 bytes 24 kHz Parm. Stereo + SBR	Packed data 17.12 kb/s Low protected: 209 bytes High protected: 5 bytes MOT slideshow 17.12 kb/s
<b>Program type</b>	Science	Varied	Other music	
<b>Links to AFS1</b>				
<b>Service</b>	aFM (no Service ID)	aFM+PI 0x467	DRM+ 0x486	
<b>Schedule</b>	Schedule 1	Schedule 1	Schedule 1	
<b>Content</b>	Different	Different	Equal	
<b>Frequency</b>	76 MHz	76 MHz	100.0 MHz	
<b>Local Information</b>				
<b>Country</b>	India	Pakistan	Afghanistan	Cameroon
<b>Language of audience</b>	Hindi	Urdu	Artificial language	Not specified
<b>Text</b>				
<b>Text headline</b>	Text Message Service 0	Text Message Service 1	Text Message Service 2	
<b>Text content</b>	Company Rohde&Schwarz Munich, Germany DRM Mode E Waveform Library	Waveform Library DRM+ ES 201 980 Rohde & Schwarz Germany, Munich	PC based DRM modulator DRM Mode E Rohde&Schwarz GmbH & Co. KG Germany, Munich	
<b>Text transmit</b>	4 times	11 times		

## 2.3.2 16QAM MSC Mapping

Describes the files with 16QAM MSC mapping and different protection levels.

### 2.3.2.1 MSC\_16QAM\_MSC\_LPP\_0\_MSC\_HPP\_0\_SDC\_1.wv

*Table 2-17: General settings*

Samples	125337600
Peak offset	4.38 dB
Peak/RMS	11.83 dB
Duration	10 minutes 52 seconds
MSC mapping	16QAM
MSC lower protection	0 (highest)
MSC higher protection	0 (highest)
SDC protection	1 (highest)

Service 2 and 3 are not available.

*Table 2-18: Services*

	Service 0	Service 1
Service ID	0xAFFD	0xAFFF
Language	Arabic	Bengali
Service label	xHE-AAC	Data PRBS
Service content	Audio xHE-AAC, 41.44 kb/s No HPP 48 kHz Stereo no SBR	PRBS 57.76 kb/s Synchronized Low protected: 629 bytes High protected: 93 bytes
Program type	News	
<b>Links to AFS1</b>		
Service	1: eFM+RDS, 0xD001 2: DAB 0xA	-
Schedule	1: None 2: Schedule 1	-
Content	1: Different 2: Different	-
Frequency	1: 96.6 MHz 2: 5A	-
<b>Local Information</b>		
Country	Afghanistan	

Language of audience	Afar	
<b>Text</b>		
Text headline	Text Message Service 0	
Text content	Rohde & Schwarz GmbH & Co. KG Munich, Germany Waveform Library DRM Mode E	
Text transmit	4 times	

### 2.3.2.2 MSC\_16QAM\_MSC\_LPP\_1\_MSC\_HPP\_1\_SDC\_1.wv

Table 2-19: General settings

Samples	125337600
Peak offset	3.93 dB
Peak/RMS	12.65 dB
Duration	10 minutes 52 seconds
MSC mapping	16QAM
MSC lower protection	1 (high)
MSC higher protection	1 (high)
SDC protection	1 (highest)

Service 1, 2 and 3 are not available.

Table 2-20: Services

	<b>Service 0</b>
Service ID	0xAFFD
Language	Chinese
Service label	xHE-AAC
Service content	Audio xHE-AAC 121.44 kb/s No HPP 48 kHz Stereo no SBR
Program type	Current affairs
<b>Links to AFS1</b>	
Service	eFM+RDS, 0xD001
Schedule	None
Content	Different

Frequency	96.6 MHz
<b>Local Information</b>	
Country	Åland Islands
Language of audience	Abkhazian
<b>Text</b>	
Text headline	Text Message Service 0
Text content	Rohde & Schwarz GmbH & Co. KG Munich, Germany Waveform Library DRM Mode E
Text transmit	4 times

### 2.3.2.3 MSC\_16QAM\_MSC\_LPP\_1\_MSC\_HPP\_1\_SDC\_0.wv

Table 2-21: General settings

Samples	125107200
Peak offset	3.68 dB
Peak/RMS	12.79 dB
Duration	10 minutes 51 seconds
MSC mapping	16QAM
MSC lower protection	1 (high)
MSC higher protection	1 (high)
SDC protection	0 (weak)

Table 2-22: Services

	Service 0	Service 1	Service 2	Service 3
Service ID	0xAFFD	0xF	0xFF	0x45A
Language	Dutch	Hindi	German	French
Service label	Audio 0 HE-AAC	Audio 1 HE-AAC	Audio 2 xHE-AAC	Audio 3 HE-AAC
Service content	Audio HE-AAC 16.32 kb/s HPP: 43 bytes 24 kHz Param. stereo + SBR	Audio HE-AAC HE-AAC 4 1.44 kb/s No HPP 24 kHz Mono + SBR	Audio xHE-AAC 14.96 kb/s No HPP 32 kHz Stereo no SBR	Audio HE-AAC 48.64 kb/s HPP 30 bytes 24 kHz Stereo + SBR
Program type	Information	Education	Science	Drama
Links to AFS1				

<b>Service</b>	eFM+RDS, D001	eFM+RDS 0xD001	eFM (no service ID)	DRM+ 0x45B
<b>Schedule</b>	None	None	None	Schedule 1
<b>Content</b>	Different	Different	Different	Equal
<b>Frequency</b>	96.6 MHz	88.9 MHz	88.9 MHz	98.5 MHz
<b>Local Information</b>				
<b>Country</b>	Albania	American Samoa	Andorra	Angola
<b>Language of audience</b>	Achinese	Acoli	Adangme	Adyghe; Adygei
<b>Text</b>				
<b>Text headline</b>	Text Message Service 0	Text Message Service 1	Text Message Service 2	Text Message Service 3
<b>Text content</b>	Munich, Germany Waveform Library DRM Mode E Rohde&Schwarz	Broadcast and media Division Rohde & Schwarz GmbH & Co. KG Mühldorfstraße 15 81671 Munich Germany	DRM Mode E Waveform Library Rohde & Schwarz Broadcast and Media Division Munich, Germany	Test ÏÓßÔöÖµþÙÚý Ÿ˘˙˚˛˜˝˞˟ˠˡˢ
<b>Text transmit</b>	4 times	6 times	4 times	10 times

### 2.3.2.4 MSC\_16QAM\_MSC\_LPP\_2\_MSC\_HPP\_1\_SDC\_1.wv

Table 2-23: General settings

<b>Samples</b>	125337600
<b>Peak offset</b>	2.61 dB
<b>Peak/RMS</b>	12.82 dB
<b>Duration</b>	10 minutes 52 seconds
<b>MSC mapping</b>	16QAM
<b>MSC lower protection</b>	2 (medium)
<b>MSC higher protection</b>	1 (high)
<b>SDC protection</b>	1 (highest)

Table 2-24: Services

	<b>Service 0</b>	<b>Service 1</b>	<b>Service 2</b>	<b>Service 3</b>
<b>Service ID</b>	0xAFFD	0xF	0xFF	0xAFFF
<b>Language</b>	Javanese	Korean	Portuguese	Not specified
<b>Service label</b>	Audio 0 HE-AAC	Audio 1 xHE-AAC	Audio 2 xHE-AAC	Data PRBS

<b>Service content</b>	Audio HE-AAC 41.44 kb/s No HPP 24 kHz Mono + SBR	Audio xHE-AAC 30.96 kb/s No HPP 38.4 kHz Stereo no SBR	Audio xHE-AAC 22.96 kb/s No HPP 32 kHz Stereo no SBR	Data PRBS 53.68 kb/s Synchronized Low protected: 671 bytes High protected: 0 bytes
<b>Program type</b>	Serious classical music	Rock Music	Easy listening music	
<b>Links to AFS1</b>				
<b>Service</b>	eFM+RDS, D001	eFM+RDS 0xD001	eFM (no service ID)	
<b>Schedule</b>	None	None	None	
<b>Content</b>	Different	Different	Different	
<b>Frequency</b>	96.6 MHz	88.9 MHz	87.5 MHz	
<b>Local Information</b>				
<b>Country</b>	Anguilla	Antarctica	Antigua and Barbuda	
<b>Language of audience</b>	Afro-Asiatic languages	Afrihili	Afrikaans	
<b>Text</b>				
<b>Text headline</b>	Text Message Service 0	Text Message Service 1	Text Message Service 2	
<b>Text content</b>	Rohde & Schwarz GmbH & Co. KG Munich, Germany Waveform Library DRM Mode E	DRM Mode E Waveform Library Rohde & Schwarz GmbH & Co. KG Munich, Germany	DRM Mode E Waveform Library Rohde & Schwarz Broadcast and Media Division Munich, Germany	
<b>Text transmit</b>	4 times	6 times	5 times	

### 2.3.2.5 MSC\_16QAM\_MSC\_LPP\_2\_MSC\_HPP\_2\_SDC\_1.wv

Table 2-25: General settings

<b>Samples</b>	125337600
<b>Peak offset</b>	3.51 dB
<b>Peak/RMS</b>	12.94 dB
<b>Duration</b>	10 minutes 52 seconds
<b>MSC mapping</b>	16QAM
<b>MSC lower protection</b>	2 (medium)

<b>MSC higher protection</b>	2 (medium)
<b>SDC protection</b>	1 (highest)

Table 2-26: Services

	<b>Service 0</b>	<b>Service 1</b>	<b>Service 2</b>	<b>Service 3</b>
<b>Service ID</b>	0xAFFD	0xF	0xFF	0xAFFF
<b>Language</b>	Russian	Korean	Portuguese	Not specified
<b>Service label</b>	Audio 0 xHE-AAC	Audio 1 HE-AAC	Audio 2 HE-AAC	Service 3 PRBS
<b>Service content</b>	Audio xHE-AAC 41.44 kb/s No HPP 48 kHz Stereo no SBR	Audio HE-AAC 16.32 kb/s HPP 43 bytes 24 kHz Param. stereo +SBR	Audio ScienceHE-AAC 16.32 kb/s HPP 43 bytes 24 kHz Param. stereo + SBR	Data PRBS 74.8 kb/s Synchronized Low protected: 935 bytes High protected: 0 bytes
<b>Program type</b>	Light classical	Other music	Science	
<b>Links to AFS1</b>				
<b>Service</b>	eFM+RDS, D001	eFM+RDS, D002	eFM (no service ID)	
<b>Schedule</b>	None	None	None	
<b>Content</b>	Different	Different	Different	
<b>Frequency</b>	96.6 MHz	88.9 MHz	87.5 MHz	
<b>Local Information</b>				
<b>Country</b>	Antigua and Barbuda	Canada	Cabo Verde	
<b>Language of audience</b>	Ainu	Dakota	Dargwa	
<b>Text</b>				
<b>Text headline</b>	Text Message Service 0	Text Message Service 1	Text Message Service 2	
<b>Text content</b>	Rohde & Schwarz GmbH & Co. KG Munich, Germany Waveform Library DRM Mode E	DRM Mode E Waveform Library Rohde & Schwarz GmbH & Co. KG Munich, Germany	DRM Mode E Waveform Library Rohde & Schwarz Broadcast and Media Division Munich, Germany	
<b>Text transmit</b>	4 times	6 times	4 times	

## 2.3.2.6 MSC\_16QAM\_MSC\_LPP\_2\_MSC\_HPP\_3\_SDC\_1.wv

Table 2-27: General settings

Samples	125337600
Peak offset	3.04 dB
Peak/RMS	12.49 dB
Duration	10 minutes 52 seconds
MSC mapping	16QAM
MSC lower protection	2 (medium)
MSC higher protection	3 (weak)
SDC protection	1 (highest)

Table 2-28: Services

	Service 0	Service 1	Service 2	Service 3
Service ID	0xAFFD	0x3FE	0x3FF	0x400
Language	Russian	Spanish	Arabic	Not specified
Service label	Audio 0 xHE-AAC	Audio 1 xHE-AAC	Audio 2 xHE-AAC	Data PRBS
Service content	Audio xHE-AAC 30.96 kb/s No HPP 38.4 kHz Stereo no SBR	Audio xHE-AAC 30.96 kb/s No HPP 38.4 kHz Stereo no SBR	Audio xHE-AAC 32.4 bit/s No HPP 38.4 kHz Stereo no SBR	Data PRBS 54.72 kb/s Low protected: 684 bytes High protected: 0 bytes
Program type	Business	Pop music	Science	
Links to AFS1				
Service	aFM (no service ID)	DAB+EEC 0x3FE	DAB 0x3FF	
Schedule	None	None	None	
Content	Different	Equal	Equal	
Frequency	78.6 MHz	5A	5A	
Local Information				
Country	Cayman Islands	Central African Republic	Chad	
Language of audience	Land Dayak languages	Caddo	Basa	
Text				
Text headline	Text Message Service 0	Text Message Service 1	Headline Service 2	

<b>Text content</b>	Rohde & Schwarz GmbH & Co. KG Munich, Germany Waveform Library DRM Mode E	DRM Mode E Waveform Library Rohde & Schwarz GmbH & Co. KG Munich, Germany	DRM+ Library Waveforms Rohde & Schwarz	
<b>Text transmit</b>	4 times	4 times	4 times	

### 2.3.2.7 MSC\_16QAM\_MSC\_LPP\_2\_MSC\_HPP\_3\_SDC\_0.wv

*Table 2-29: General settings*

<b>Samples</b>	125337600
<b>Peak offset</b>	3.03 dB
<b>Peak/RMS</b>	12.43 dB
<b>Duration</b>	10 minutes 52 seconds
<b>MSC mapping</b>	16QAM
<b>MSC lower protection</b>	2 (medium)
<b>MSC higher protection</b>	3 (weak)
<b>SDC protection</b>	0 (weak)

*Table 2-30: Services*

	<b>Service 0</b>	<b>Service 1</b>	<b>Service 2</b>	<b>Service 3</b>
<b>Service ID</b>	0xC1D2	0x467	0x468	0x469
<b>Language</b>	Hindi	Dutch	Chinese	Bengali
<b>Service label</b>	Audio 0 xHE-AAC	Audio 1 xHE-AAC	Audio 2 HE-AAC	Data slideshow
<b>Service content</b>	Audio xHE-AAC 30.96 kb/s No HPP 38.4 kHz Stereo no SBR	Audio xHE-AAC 41.44 kb/s No HPP 48 kHz Stereo no SBR	Audio HE-AAC 29.12 kb/s No HPP 24 kHz Param. stereo + SBR	Packed data 48.16 kb b Low protected: 557 Bytes High protected: 45 bytes Packet size: 258 bytes MOT slideshow 41.28 kb/s
<b>Program type</b>	Science	Varied	Other music	
<b>Links to AFS1</b>				
<b>Service</b>	aFM +PI 0xC1D2	aFM (no service ID)	eFM+ECC 0x468	
<b>Schedule</b>	None	Schedule 2	Schedule 1	
<b>Content</b>	Different	Different	Different	

<b>Frequency</b>	76 MHz	76 MHz	87.5 MHz	
<b>Local Information</b>				
<b>Country</b>	India	Pakistan	Afghanistan	Cameroon
<b>Language of audience</b>	Hindi	Urdu	Artificial language	Not specified
<b>Text</b>				
<b>Text headline</b>	Text Message Service 0	Text Message Service 1	Text Message Service 2	
<b>Text content</b>	Company Rohde&Schwarz Munich, Germany DRM Mode E Waveform Library	Waveform Library DRM+ ES 201 980 Rohde & Schwarz Germany, Munich	PC based DRM modulator DRM Mode E Rohde&Schwarz GmbH & Co. KG Germany, Munich	
<b>Text transmit</b>	4 times	11 times		

### 2.3.2.8 MSC\_16QAM\_MSC\_LPP\_3\_MSC\_HPP\_3\_SDC\_0.wv

*Table 2-31: General settings*

<b>Samples</b>	125337600
<b>Peak offset</b>	3.37 dB
<b>Peak/RMS</b>	12.76 dB
<b>Duration</b>	10 minutes 52 seconds
<b>MSC mapping</b>	16QAM
<b>MSC lower protection</b>	3 (weak)
<b>MSC higher protection</b>	3 (weak)
<b>SDC protection</b>	0 (weak)

*Table 2-32: Services*

	<b>Service 0</b>	<b>Service 1</b>	<b>Service 2</b>	<b>Service 3</b>
<b>Service ID</b>	0xC1D2	0x467	0x468	0x469
<b>Language</b>	French	Arabic	Chinese	German
<b>Service label</b>	Service0 xHE-AAC	Service1 HE-AAC	Service2 HE-AAC	Data slideshow

<b>Service content</b>	Audio xHE-AAC 41.44 kb/s No HHP 48 kHz Stereo no SBR	Audio HE-AAC 48.64 kb/s HHP 30 Bytes 24 kHz Stereo + SBR	Audio HE-AAC 31.2 kb/s HHP 78 bytes 24 kHz Stereo + SBR	Packed data 64.72 kb/s Low protected: 804 bytes High protected: 5 bytes Packet size: 258 bytes MOT slideshow 61.92 kb/s
<b>Program type</b>	Science	Varied	Other music	
<b>Links to AFS1</b>				
<b>Service</b>	aFM (no Service ID)	aFM+PI 0x467	DRM+ 0x496	
<b>Schedule</b>	Schedule 1	Schedule 1	Schedule 1	
<b>Content</b>	Different	Different	Equal	
<b>Frequency</b>	76 MHz	76 MHz	100.0 MHz	
<b>Local Information</b>				
<b>Country</b>	India	Pakistan	Germany	Cameroon
<b>Language of audience</b>	Hindi	Urdu	Artificial language	Not specified
<b>Text</b>				
<b>Text headline</b>	Text Message Service 0	Text Message Service 1	Text Message Service 2	
<b>Text content</b>	Company Rohde&Schwarz Munich, Germany DRM Mode E Waveform Library	Waveform Library DRM+ ES 201 980 Rohde & Schwarz Germany, Munich	PC based DRM modulator DRM Mode E Rohde&Schwarz GmbH & Co. KG Germany, Munich	
<b>Text transmit</b>	4 times	11 times	11 times	

## 2.4 DRM Services

All files of this group have DRM settings as follows:

- MSC mapping: 16QAM
- MSC lower protection: 2 (medium)
- MSC higher protection: 2 (medium)
- SDC protection: 1 (highest)

## 2.4.1 Services\_1\_AAC.wv

**Table 2-33: General settings**

<b>Samples</b>	125337600
<b>Peak offset</b>	3.11 dB
<b>Peak/RMS</b>	12.26 dB
<b>Duration</b>	10 minutes 52 seconds

Service 1, 2 and 3 are not available.

**Table 2-34: Services**

	<b>Service 0</b>
<b>Service ID</b>	0xABCD
<b>Language</b>	Japanese
<b>Service label</b>	Sweep 20 Hz 20 kHz
<b>Service content</b>	Audio AAC 149.04 kb/s HHP: 377 bytes
<b>Program type</b>	Science
<b>Links to AFS1</b>	
<b>Service</b>	DAB data 0x3ED
<b>Schedule</b>	None
<b>Content</b>	Different
<b>Frequency</b>	5A
<b>Local Information</b>	
<b>Country</b>	Åland Islands
<b>Language of audience</b>	Acoli
<b>Text</b>	
<b>Text headline</b>	Headline Service 0
<b>Text content</b>	Test wave sweep sine 20 Hz to 20 kHz Duration 20 s
<b>Text transmit</b>	4 times

## 2.4.2 Services\_2\_HE-AAC\_xHE-AAC.wv

Table 2-35: General settings

Samples	125337600
Peak offset	3.41 dB
Peak/RMS	12.65 dB
Duration	10 minutes 52 seconds

Service 2 and 3 are not available.

Table 2-36: Services

	Service 0	Service 1
Service ID	0xBCDE	0xBCDF
Language	Portuguese	Other Language
Service label	Audio0 HE-AAC	Audio 1 xHE-AAC
Service content	Audio HE-AAC 121.44 kb/s HPP: 307 bytes 48 kHz Stereo no SBR	Audio xHE-AAC 27.6 kb/s No HPP 38.4 kHz Stereo no SBR
Program type	Science	Rock music
<b>Links to AFS1</b>		
Service	eFM+EEC, BCDE	
Schedule	None	
Content	Equal	
Frequency	87.5 MHz	
<b>Local Information</b>		
Country	Yemen	Western Sahara
Language of audience	Zande languages	Zenaga
<b>Text</b>		
Text headline	Headline Service 0	Headline Service 1
Text content	Mozart 121.44 kbit/s HE-AAC 48 kHz Stereo, no SBR	Schadstoff Rock xHE-AAC 28.24 kbit/s Stereo
Text transmit	4 times	4 times

### 2.4.3 Services\_2\_HE-AAC\_AAC.wv

Table 2-37: General settings

Samples	125337600
Peak offset	4.10 dB
Peak/RMS	12.42 dB
Duration	10 minutes 52 seconds

Service 2 and 3 are not available.

Table 2-38: Services

	Service 0	Service 1
Service ID	0xCEEE	0x3FB
Language	Russian	Korean
Service label	Audio 0 HE-AAC	Audio AAC
Service content	Audio HE-AAC 61.84 kb/s HPP 157 bytes 48 kHz Stereo no SBR	Audio AAC 87.2 kb/s HPP 227 bytes Mono
Program type	Light classical	Other music
<b>Links to AFS1</b>		
Service	aFM+Pi, 0xCEEE	eFM+RDS, 0x3FB
Schedule	Schedule 1	None
Content	Different	Equal
Frequency	76 MHz	87.5 MHz
<b>Local Information</b>		
Country	Vietnam	Venezuela
Language of audience	Yupik languages	Yoruba
<b>Text</b>		
Text headline	Text Message Service 0	Sweep 20 Hz 20 kHz
Text content	Rohde & Schwarz GmbH & Co. KG Munich, Germany Waveform Library DRM Mode E	Sine sweep 20 Hz to 20 kHz Duration 20 s AAC 87.2 kbit/s HPP = 227 bytes
Text transmit	4 times	4 times

### 2.4.4 Services\_3\_HE-AAC\_AAC\_PRBS.wv

<b>Samples</b>	125337600
<b>Peak offset</b>	3.22 dB
<b>Peak/RMS</b>	12.42 dB
<b>Duration</b>	10 minutes 52 seconds

Service 3 is not available.

**Table 2-39: Services**

	<b>Service 0</b>	<b>Service 1</b>	<b>Service 2</b>
<b>Service ID</b>	0x3F1	0x3EA	0x3EB
<b>Language</b>	Korean	Javanese	German
<b>Service label</b>	Audio HE-AAC	Audio AAC	Data PRBS
<b>Service content</b>	Audio HE-AAC 74.48 kb/s HPP 188 bytes 24 kHz Stereo + SBR	Audio HE-AAC 37.28 kb/s HPP 93 bytes Mono	PRBS Synchronized 37.28 kb/s HPP 0 bytes
<b>Program type</b>	Other music	Science	
<b>Links to AFS1</b>			
<b>Service</b>	aFM (no service ID)	DAB+EEC 0x3EA	
<b>Schedule</b>	None	None	
<b>Content</b>	Different	Equal	
<b>Frequency</b>	76 MHz	5A	
<b>Local Information</b>			
<b>Country</b>	Vanuata	Uzbekistan	
<b>Language of audience</b>	Yiddish	Yapese	
<b>Text</b>			
<b>Text headline</b>	Headline Service 0	Headline Service 1	
<b>Text content</b>	Mozart HE-AAC 74.48 kbit/s HPP 188 bytes 24 kHz stereo	Sweep audio 20 Hz to 20 kHz 20 seconds Audio AAC 37.28 kbit/s HPP 28 bytes	
<b>Text transmit</b>	4 times	4 times	

## 2.4.5 Services\_3\_HE-AAC\_HE-AAC\_PRBS.wv

Table 2-40: General Settings

Samples	125337600
Peak offset	2.96 dB
Peak/RMS	12.89 dB
Duration	10 minutes 52 seconds

Service 3 is not available.

Table 2-41: Services

	Service 0	Service 1	Service 2
Service ID	0xC111	0x3EA	0x3EB
Language	Arabic	Javanese	Other Language
Service label	Audio Sweep HE	Audio 1 Rock	Data PRBS
Service content	Audio HE-AAC 61.84 kb/s HPP 157 bytes 48 kHz Stereo no SBR	Audio HE-AAC 43.6 kb/s HPP 113 bytes 24 kHz Stereo + SBR	Data PRBS Synchronized 43.6 kb/s No HHP
Program type	Science	Varied	
<b>Links to AFS1</b>			
Service	aFM (no Service ID)	eFM (no service ID)	
Schedule	None	None	
Content	Different	Equal	
Frequency	76 MHz	87.5 MHz	
<b>Local Information</b>			
Country	Uruguay	Tuvalu	
Language of audience	Yao	Xhosa	
<b>Text</b>			
Text headline	Headline Text 0	Headline Service 1	
Text content	Coding HE-AAC 61.84 kbit/s HPP 187 bytes 48 kHz Stereo, no SBR	Mozart HE-AAC 43.6 kbit/s HPP 113 bytes 24 kHz stereo SBR	
Text transmit	4 times	8 times	

## 2.4.6 Services\_4\_xHE-AAC\_xHE-AAC\_xHE-AAC\_xHE-AAC.wv

Table 2-42: General settings

Samples	125337600
Peak offset	3.77 dB
Peak/RMS	13.11 dB
Duration	10 minutes 52 seconds

Table 2-43: Services

	Service 0	Service 1	Service 2	Service 3
Service ID	0xA001	0xA002	0xA003	A004
Language	Other language	Dutch	French	Hindi
Service label	Audio0 xHE-AAC	Audio1 xHE-AAC	Audio2 xHE-AAC	Audio3 xHE-AAC
Service content	Audio xHE-AAC 30.96 kb/s No HPP 38.4 kHz Stereo no SBR	Audio xHE-AAC 27.92 kb/s No HPP 38.4 kHz Stereo no SBR	Audio xHE-AAC 41.44 kb/s No HPP 48 kHz Stereo no SBR	Audio xHE-AAC 27.92 kb/s No HPP 38.4 kHz Stereo no SBR
Program type	Other music	Rock Music	Serious classical	Varied
<b>Links to AFS1</b>				
Service	aFM (no service ID)	AM+AMSS	AM (no service ID)	aFM+PI 0xA004
Schedule	None	None	None	None
Content	Different	Equal	Equal	Equal
Frequency	76 MHz	6.95 MHz	6.75 MHz	76 MHz
<b>Local Information</b>				
Country	Turkey	Tunisia	Trinidad and Tobago	Tonga
Language of audience	Walloon	Sorbian languages	Welsh	Washo
<b>Text</b>				
Text headline	Headline Service 0	Headline Service 1	Headline Service 2	

<b>Text content</b>	Martin Luther King (speech) Coding xHE-AAC 30.96 kbit/s No HPP 38.4 kHz Stereo, no SBR	Schadstoff Rock Coding xHE-AAC 27.92 kbit/s No HPP 38.4 kHz Stereo no SBR	Mozart Coding xHE-AAC 41.44 kbit/s No HPP 48 kHz Stereo no SBR	Schadstoff Rock Coding xHE-AAC 27.92 kbit/s No HPP 32.8 kHz Stereo no SBR
<b>Text transmit</b>	4 times	4 times	4 times	4 times

## 2.5 EN 303 345 DRM Testing

The files in this folder are for DRM testing according to EN 303 345-5 v0.0.5. Table 1 in this standard defines the required parameters.

The proposed test cases are defined for three different frequency bands:

- LFMF
- HF
- VHF

For each frequency band, two signals are required:

- Wanted signal (1 kHz sine)
- Unwanted signal (2 kHz sine)

The LFMF band and the HF band use robustness mode B. The VHF band uses robustness mode E.

This waveform library (R&S SMCVB-KV12) contains only DRM test signals that use robustness mode E. They are described in [Chapter 2.5.1, "VHF\\_wanted.wv"](#), on page 35 and [Chapter 2.5.2, "VHF\\_unwanted.wv"](#), on page 36.

DRM test signals using robustness mode B are part of the waveform library R&S SMCVB-KV11 DRM Waveforms (1434.5370.xx)..

### 2.5.1 VHF\_wanted.wv

*Table 2-44: General settings*

<b>Samples</b>	53683200
<b>Peak offset</b>	0 dB
<b>Peak/RMS</b>	12.11 dB
<b>Duration</b>	6 minutes 59 seconds

*Table 2-45: Services*

	<b>Service 0</b>
<b>Service ID</b>	0x1001

Language	English
Service label	"Sine 1 kHz"
Program type	Other Music
Country	United Kingdom
Language of audience	English

Table 2-46: Audio Parameters

Parameter	Service 0
Audio Signal	1 kHz tone, -3 dBFs
Audio Coding	AAC
Audio Mode	Mono
SBR	Disabled
Sampling rate	48 kHz
Bit rate	149040 bps

## 2.5.2 VHF\_unwanted.wv

Table 2-47: General settings

Samples	53683200
Peak offset	0 dB
Peak/RMS	12.11 dB
Duration	6 minutes 59 seconds

Table 2-48: Services

	Service 0
Service ID	0x1001
Language	English
Service label	"Sine 2 kHz"
Program type	Other Music
Country	United Kingdom
Language of audience	English

Table 2-49: Audio Parameters

Parameter	Service 0
Audio Signal	2 kHz tone, -3 dBFs
Audio Coding	AAC
Audio Mode	Mono

<b>SBR</b>	Disabled
<b>Sampling rate</b>	48 kHz
<b>Bit rate</b>	149040 bps

# Index

## A

Application cards .....	7
Application notes .....	7

## B

Brochures .....	6
-----------------	---

## D

Data sheets .....	6
Documentation overview .....	5

## G

Getting started .....	5
-----------------------	---

## H

Help .....	5
------------	---

## I

Installation .....	5
Instrument help .....	5
Instrument security procedures .....	6

## K

Key features .....	5
--------------------	---

## O

Open source acknowledgment (OSA) .....	7
--	---

## R

Release notes .....	7
---------------------	---

## S

Safety instructions .....	6
Security procedures .....	6
Service manual .....	6

## U

User manual .....	5
-------------------	---

## W

Waveform files .....	8
Welcome .....	5
White papers .....	7